

**Micro Commercial Components** 

Micro Commercial Components 20736 Marilla Street Chatsworth CA 91311 Phone: (818) 701-4933 (818) 701-4939 Fax:

- Features
  Case Material: Molded Plastic. UL Flammability Classification
- Rating 94V-0 and MSL Rating 1 Built-in bias resistors enable the configuration of an inverter circuit without connecting external input resistors
- The bias resistors consist of thin-film resistors with complete . isolation to allow negative biasing of the input. They also have the advantage of almost completely eliminating parasitic effects.
- Only the on/off conditions need to be set for operation, making • device design easy


#### Absolute maximum ratings @ 25°C

Symbol	Parameter	Min	Тур	Max	Unit
V <sub>cc</sub>	Supply voltage		50		V
V <sub>IN</sub>	Input voltage	-6		40	V
I <sub>O</sub> I <sub>C(MAX)</sub>	Output current		70 100		mA
Pd	Power dissipation		200		mW
Tj	Junction temperature		150		°C
T <sub>stg</sub>	Storage temperature	-55		150	°C

#### Electrical Characteristics @ 25°C

Symbol	Parameter	Min	Тур	Max	Unit
V <sub>I(off)</sub>	Input voltage (V <sub>CC</sub> =5V, I <sub>O</sub> =100 µ A)			0.3	V
V <sub>I(on)</sub>	(V <sub>o</sub> =0.3V, I <sub>o</sub> =1mA)	1.4			V
V <sub>O(on)</sub>	Output voltage (I <sub>0</sub> /I <sub>1</sub> =5mA/0.25mA)		0.1	0.3	V
I <sub>I</sub>	Input current (V <sub>i</sub> =5V)			0.88	mA
I <sub>O(off)</sub>	Output current (V <sub>CC</sub> =50V, V <sub>I</sub> =0)			0.5	μA
G	DC current gain (V <sub>0</sub> =5V, I <sub>0</sub> =5mA)	68			
R <sub>1</sub>	Input resistance	7.0	10	13	KΩ
R <sub>2</sub> /R <sub>1</sub>	Resistance ratio	3.7	4.7	5.7	
f <sub>T</sub>	Transition frequency (V <sub>CE</sub> =10V, I <sub>E</sub> =5mA, f=100MHz)		250		MHz

#### Equivalent circuit



#### SOT-323 D 3 🕂 1: IN 2: GND B 3: OUT 2 F DIMENSIONS INCHES NOTE DIM MIN MAX MIN MAX .071 .087 1.80 2.20 A В .045 .053 1.15 1.35 С .079 087 2 00 2.20 D .026 Nominal 0.65Nominal E .047 .055 1.20 1.40 F .012 .016 40 G .000 .004 .000 .100 Н .035 .039 .90 1.00 .004 .010 .100 .250 J Κ .012 .016 .40 .30 Suggested Solder Pad Layout 0.70 0.90 1 90 0.65 0.65

## www.mccsemi.com

#### **Revision: 2**

Downloaded from Elcodis.com electronic components distributor

2008/01/01

### DTC114YUA

NPN

**Digital Transistors** 



### **Ordering Information**

Device	Packing
(Part Number)-TP	Tape&Reel3Kpcs/Reel

### \*\*\*IMPORTANT NOTICE\*\*\*

Micro Commercial Components Corp. reserves the right to make changes without further notice to any product herein to make corrections, modifications, enhancements, improvements, or other changes.
 Micro Commercial Components Corp. does not assume any liability arising out of the application or use of any product described herein; neither does it convey any license under its patent rights ,nor the rights of others. The user of products in such applications shall assume all risks of such use and will agree to hold Micro Commercial Components Corp. and all the companies whose products are represented on our website, harmless against all damages.

#### \*\*\*APPLICATIONS DISCLAIMER\*\*\*

Products offer by Micro Commercial Components Corp. are not intended for use in Medical,

Aerospace or Military Applications.

# www.mccsemi.com