

SANYO**SB05-05CP**

Shottky Barrier Diode

50V, 500mA Rectifier**Applications**

- High frequency rectification (switching regulators, converters, choppers).


Features

- Low forward voltage (V_F max=0.55V).
- Fast reverse recovery time (t_{rr} max=10ns).
- Low switching noise.
- Low leakage current and high reliability due to highly reliable planar structure.

Package Dimensions

unit:mm

1148


**Specifications****Absolute Maximum Ratings at $T_a = 25^\circ\text{C}$**

| Parameter | Symbol | Conditions | Ratings | Unit |
|--|-----------|------------------------|-------------|------------------|
| Repetitive Peak Reverse Voltage | V_{RRM} | | -50 | V |
| Nonrepetitive Peak Reverse Surge Voltage | V_{RSM} | | -55 | V |
| Average Output Current | I_O | | 500 | mA |
| Surge Forward Current | I_{FSM} | 50Hz sine wave, 1cycle | 5 | A |
| Junction Temperature | T_J | | -55 to +125 | $^\circ\text{C}$ |
| Storage Temperature | T_{stg} | | -55 to +125 | $^\circ\text{C}$ |

Electrical Characteristics at $T_a = 25^\circ\text{C}$

| Parameter | Symbol | Conditions | Ratings | | | Unit |
|---------------------------|-----------|--|---------|-----|------|--------------------|
| | | | min | typ | max | |
| Reverse Voltage | V_R | $I_R = -200\mu\text{A}$ | -50 | | | V |
| Forward Voltage | V_F | $I_F = -500\text{mA}$ | | | 0.55 | V |
| Reverse Current | I_R | $V_R = -25\text{V}$ | | | -50 | μA |
| Interterminal Capacitance | C | $V_R = -10\text{V}$, $f = 1\text{MHz}$ | | 17 | | pF |
| Reverse Recovery Time | t_{rr} | $I_F = I_R = 100\text{mA}$, See specified Test Circuit | | | 10 | ns |
| Thermal Resistance | Rthj-a(1) | | | 420 | | $^\circ\text{C/W}$ |
| | Rthj-a(2) | Mounted on Cu-foild area of $16\text{mm}^2 \times 0.2\text{mm}$ on glass epoxy board | | 330 | | $^\circ\text{C/W}$ |






· Marking:B

 t_{rr} Test Circuit**SANYO Electric Co.,Ltd. Semiconductor Bussiness Headquarters**

TOKYO OFFICE Tokyo Bldg., 1-10, 1 Chome, Ueno, Taito-ku, TOKYO, 110-8534 JAPAN

33098HA (KT)/1239TA/O255KI, TS No.1917-1/2

SB05-05CP



- No products described or contained herein are intended for use in surgical implants, life-support systems, aerospace equipment, nuclear power control systems, vehicles, disaster/crime-prevention equipment and the like, the failure of which may directly or indirectly cause injury, death or property loss.
- Anyone purchasing any products described or contained herein for an above-mentioned use shall:
 - ① Accept full responsibility and indemnify and defend SANYO ELECTRIC CO., LTD., its affiliates, subsidiaries and distributors and all their officers and employees, jointly and severally, against any and all claims and litigation and all damages, cost and expenses associated with such use:
 - ② Not impose any responsibility for any fault or negligence which may be cited in any such claim or litigation on SANYO ELECTRIC CO., LTD., its affiliates, subsidiaries and distributors or any of their officers and employees jointly or severally.
- Information (including circuit diagrams and circuit parameters) herein is for example only; it is not guaranteed for volume production. SANYO believes information herein is accurate and reliable, but no guarantees are made or implied regarding its use or any infringements of intellectual property rights or other rights of third parties.

This catalog provides information as of March, 1998. Specifications and information herein are subject to change without notice.