DATA SHEET



JUNCTION FIELD EFFECT TRANSISTOR 2SK508

HIGH FREQUENCY AMPLIFIER N-CHANNEL SILICON JUNCTION FIELD EFFECT TRANSISTOR

<R> DESCRIPTION

The 2SK508 is low input capacitance and High forward transfer admittance, it is suitable for AM tuner, wireless installation and cordless telephone.

<R> FEATURES

• Low input capacitance

 $C_{iss} = 4.8 pF TYP. (V_{DS} = 5.0 V, I_{D} = 10 mA, f = 1.0 MHz)$


• High forward transfer admittance

 $| y_{fs} | 2 = 26 \text{ mS TYP.} (V_{DS} = 5.0 \text{ V}, V_{GS} = 0 \text{ V}, f = 1.0 \text{ kHz})$

<R> ORDERING INFORMATION

PART NUMBER	PACKAGE		
2SK508	SC-59 (Mini Mold)		

PACKAGE DRAWING (Unit: mm)



ABSOLUTE MAXIMUM RATINGS (TA = 25°C)

Gate to Drain Voltage	Vgdo	−15	V
Gate to Source Voltage	Vgso	-15	V
Drain to Source Voltage (VGS = -4.0 V)	V_{DSX}	15	V
Drain Current (DC)	lσ	50	mA
Gate Current (DC)	lg	5	mA
Total Power Dissipation	Рт	200	mW
Junction Temperature	Tj	150	°C
Storage Temperature	Tstg	-55 to +150	°C

The information in this document is subject to change without notice. Before using this document, please confirm that this is the latest version.

Not all products and/or types are available in every country. Please check with an NEC Electronics sales representative for availability and additional information.

Document No. D18962EJ2V0DS00 (2nd edition) (Previous No. TC-1651)
Date Published December 2007 NS

ELECTRICAL CHARACTERISTICS (TA = 25°C)

CHARACTERISTICS	SYMBOL	TEST CONDITIONS	MIN.	TYP.	MAX.	UNIT
Gate Cut-off Current	Igss	V _{GS} = -10 V, V _{DS} = 0 V			-1.0	nA
Zero Gate Voltage Drain Current Note	IDSS	loss V _{DS} = 5.0 V, V _{GS} = 0 V		20	50	mA
Gate to Source Cut-off Voltage	V _{GS(off)}	$V_{DS} = 5.0 \text{ V}, I_{D} = 10 \mu\text{A}$	-0.6	-1.4	-3.5	V
Forward Transfer Admittance Note	y _{fs} 1	V _{DS} = 5.0 V, I _D = 10 mA, f = 1.0 kHz	14	19		mS
	y _{fs} 2	V _{DS} = 5.0 V, V _{GS} = 0 V, f = 1.0 kHz	14	26		mS
Input Capacitance	Ciss	V _{DS} = 5.0 V, I _D = 10 mA, f = 1.0 MHz		4.8		pF
Feedback Capacitance	Crss	V _{DS} = 5.0 V, I _D = 10 mA, f = 1.0 MHz		1.6		pF

Note Pulsed: PW \leq 1 ms, Duty Cycle \leq 1%

IDSS CLASSIFICATION


MARKING	K51	K52	K53
Ibss (mA)	10 to 20	15 to 30	25 to 50


NEC

P⊤ - Total Power Dissipation - mW


Ib - Drain Current - mA

TYPICAL CHARACTERISTICS (TA = 25°C)






DRAIN CURRENT vs.
DRAIN TO SOURCE VOLTAGE




T_A - Ambient Temperature - °C


DRAIN CURRENT vs. GATE TO SOURCE VOLTAGE




GATE TO SOURCE CUT-OFF VOLTAGE vs. ZERO GATE VOLTAGE DRAIN CURRENT



FORWARD TRANSFER ADMITTANCE vs. ZERO GATE VOLTAGE DRAIN CURRENT



INPUT AND FEEDBACK CAPACITANCE vs. DRAIN TO SOURCE VOLTAGE



- The information in this document is current as of December, 2007. The information is subject to change without notice. For actual design-in, refer to the latest publications of NEC Electronics data sheets or data books, etc., for the most up-to-date specifications of NEC Electronics products. Not all products and/or types are available in every country. Please check with an NEC Electronics sales representative for availability and additional information.
- No part of this document may be copied or reproduced in any form or by any means without the prior
 written consent of NEC Electronics. NEC Electronics assumes no responsibility for any errors that may
 appear in this document.
- NEC Electronics does not assume any liability for infringement of patents, copyrights or other intellectual
 property rights of third parties by or arising from the use of NEC Electronics products listed in this document
 or any other liability arising from the use of such products. No license, express, implied or otherwise, is
 granted under any patents, copyrights or other intellectual property rights of NEC Electronics or others.
- Descriptions of circuits, software and other related information in this document are provided for illustrative purposes in semiconductor product operation and application examples. The incorporation of these circuits, software and information in the design of a customer's equipment shall be done under the full responsibility of the customer. NEC Electronics assumes no responsibility for any losses incurred by customers or third parties arising from the use of these circuits, software and information.
- While NEC Electronics endeavors to enhance the quality, reliability and safety of NEC Electronics products, customers agree and acknowledge that the possibility of defects thereof cannot be eliminated entirely. To minimize risks of damage to property or injury (including death) to persons arising from defects in NEC Electronics products, customers must incorporate sufficient safety measures in their design, such as redundancy, fire-containment and anti-failure features.
- NEC Electronics products are classified into the following three quality grades: "Standard", "Special" and "Specific".
 - The "Specific" quality grade applies only to NEC Electronics products developed based on a customerdesignated "quality assurance program" for a specific application. The recommended applications of an NEC Electronics product depend on its quality grade, as indicated below. Customers must check the quality grade of each NEC Electronics product before using it in a particular application.
 - "Standard": Computers, office equipment, communications equipment, test and measurement equipment, audio and visual equipment, home electronic appliances, machine tools, personal electronic equipment and industrial robots
 - "Special": Transportation equipment (automobiles, trains, ships, etc.), traffic control systems, anti-disaster systems, anti-crime systems, safety equipment and medical equipment (not specifically designed for life support).
 - "Specific": Aircraft, aerospace equipment, submersible repeaters, nuclear reactor control systems, life support systems and medical equipment for life support, etc.

The quality grade of NEC Electronics products is "Standard" unless otherwise expressly specified in NEC Electronics data sheets or data books, etc. If customers wish to use NEC Electronics products in applications not intended by NEC Electronics, they must contact an NEC Electronics sales representative in advance to determine NEC Electronics' willingness to support a given application.

(Note)

- (1) "NEC Electronics" as used in this statement means NEC Electronics Corporation and also includes its majority-owned subsidiaries.
- (2) "NEC Electronics products" means any product developed or manufactured by or for NEC Electronics (as defined above).