

GT80J101B

High Power Switching Applications

- Enhancement mode type
- High speed: $t_f = 0.40 \mu s$ (max) ($I_C = 80 A$)
- Low saturation voltage: $V_{CE(sat)} = 2.9 V$ (max) ($I_C = 80 A$)

Maximum Ratings ($T_a = 25^\circ C$)


Characteristics	Symbol	Rating	Unit
Collector-emitter voltage	V_{CES}	600	V
Gate-emitter voltage	V_{GES}	± 20	V
Continuous collector current	@ $T_c = 100^\circ C$	33	A
	@ $T_c = 25^\circ C$	80	
Pulsed collector current (Note 1)	I_{CP}	160	A
Collector power dissipation	@ $T_c = 100^\circ C$	80	W
	@ $T_c = 25^\circ C$	200	
	@ $T_a = 25^\circ C$	3.5	
Junction temperature	T_j	150	$^\circ C$
Storage temperature	T_{stg}	-55~150	$^\circ C$
Screw torque	—	0.8	N·m

Note 1: The Maximum rating of $I_{CP}=160A$ is limited by pulse (1ms).
Refer to the graph of safe operating area for the detail.


Thermal Characteristics

Characteristics	Symbol	Rating	Unit
Thermal resistance , junction to case ($T_c = 25^\circ C$)	$R_{th(j-c)}$	0.625	$^\circ C/W$
Thermal resistance , junction to air ($T_a = 25^\circ C$)	$R_{th(j-a)}$	35.7	$^\circ C/W$

MARKING



Unit: mm




JEDEC	?
JEITA	?
TOSHIBA	2-21F2C

Weight: 9.75 g (typ.)

Electrical Characteristics (Ta = 25°C)







Characteristics		Symbol	Test Condition	Min	Typ.	Max	Unit
Gate leakage current		I_{GES}	$V_{GE} = \pm 25\text{ V}, V_{CE} = 0$	—	—	± 500	nA
Collector cut-off current		I_{CES}	$V_{CE} = 600\text{ V}, V_{GE} = 0$	—	—	1.0	mA
Gate-emitter cut-off voltage		$V_{GE (OFF)}$	$V_{CE} = 5\text{ V}, I_C = 80\text{ mA}$	3.0	—	6.0	V
Collector-emitter saturation voltage		$V_{CE (sat) (1)}$	$I_C = 10\text{ A}, V_{GE} = 15\text{ V}$	—	—	2.0	V
		$V_{CE (sat) (2)}$	$I_C = 80\text{ A}, V_{GE} = 15\text{ V}$	—	2.4	2.9	
Input capacitance		C_{ies}	$V_{CE} = 10\text{ V}, V_{GE} = 0, f = 1\text{ MHz}$	—	5500	—	pF
Switching time	Rise time	t_r	Resistive load $V_{CC} = 300\text{ V}, I_C = 80\text{ A}$ $V_{GG} = \pm 15\text{ V}, R_G = 33\Omega$ (Note 2)	—	0.3	—	μs
	Turn-on time	t_{on}		—	0.5	—	
	Fall time	t_f		—	0.25	0.40	
	Turn-off time	t_{off}		—	0.7	—	







Note 2: Switching time measurement circuit and input/output waveforms.




Caution on handling

This device is MOS gate type. Therefore, please care about ESD when use.







RESTRICTIONS ON PRODUCT USE

030619EAA

- The information contained herein is subject to change without notice.
- The information contained herein is presented only as a guide for the applications of our products. No responsibility is assumed by TOSHIBA for any infringements of patents or other rights of the third parties which may result from its use. No license is granted by implication or otherwise under any patent or patent rights of TOSHIBA or others.
- TOSHIBA is continually working to improve the quality and reliability of its products. Nevertheless, semiconductor devices in general can malfunction or fail due to their inherent electrical sensitivity and vulnerability to physical stress. It is the responsibility of the buyer, when utilizing TOSHIBA products, to comply with the standards of safety in making a safe design for the entire system, and to avoid situations in which a malfunction or failure of such TOSHIBA products could cause loss of human life, bodily injury or damage to property.
In developing your designs, please ensure that TOSHIBA products are used within specified operating ranges as set forth in the most recent TOSHIBA products specifications. Also, please keep in mind the precautions and conditions set forth in the "Handling Guide for Semiconductor Devices," or "TOSHIBA Semiconductor Reliability Handbook" etc..
- The TOSHIBA products listed in this document are intended for usage in general electronics applications (computer, personal equipment, office equipment, measuring equipment, industrial robotics, domestic appliances, etc.). These TOSHIBA products are neither intended nor warranted for usage in equipment that requires extraordinarily high quality and/or reliability or a malfunction or failure of which may cause loss of human life or bodily injury ("Unintended Usage"). Unintended Usage include atomic energy control instruments, airplane or spaceship instruments, transportation instruments, traffic signal instruments, combustion control instruments, medical instruments, all types of safety devices, etc.. Unintended Usage of TOSHIBA products listed in this document shall be made at the customer's own risk.
- TOSHIBA products should not be embedded to the downstream products which are prohibited to be produced and sold, under any law and regulations.