



IF Filters for CDMA Cellular Phones

Series/Type: **B7305**

The following products presented in this data sheet are being withdrawn.

Ordering Code	Substitute Product	Date of Withdrawal	Deadline Last Orders	Last Shipments
B39191B7305A810	B39191B5006H310	2005-05-13	2005-06-30	2005-09-30

For further information please contact your nearest EPCOS sales office, which will also support you in selecting a suitable substitute. The addresses of our worldwide sales network are presented at www.epcos.com/sales.



SAW Components

Data Sheet B7305






DCS10A Chip-Size SAW Filter Package

Features

- IF filter for mobile telephone
- Channel selection in W-CDMA systems
- Chip-Size SAW Filter Package
- Balanced and unbalanced operation possible
- Package for Surface Mounted Technology (SMT)

Terminals


- Gold-plated Ni



Dimensions in mm, approx. weight 0,1 g

Pin configuration

- 9 Input
- 10 Balanced input or input ground
- 4 Output
- 5 Balanced output or output ground
- 1, 2, 6, 7 To be grounded
- 3, 8 Case – ground



Type	Ordering code	Marking and Package according to	Packing according to
B7305	B39191-B7305-A810	C61157-A7-A66	F61074-V8103-Z000

Electrostatic Sensitive Device (ESD)

Maximum ratings

Operating temperature range	T	-20 / +85	°C	
Storage temperature range	T_{stg}	-40 / +85	°C	
DC voltage	V_{DC}	0	V	
Source power	P_s	10	dBm	



Data Sheet



Characteristics¹⁾

Operating temperature range: $T = 25\text{ °C}$
 Terminating source impedance: $Z_S = 0,9\text{ k}\Omega \parallel 60\text{ nH}$
 Terminating load impedance: $Z_L = 1,1\text{ k}\Omega \parallel 90\text{ nH}$

		min.	typ.	max.	
Nominal frequency	f_N	—	190,0	—	MHz
Minimum insertion attenuation (including losses in matching circuit)	α_{\min}		8,8	9,2	dB
Passband width $\alpha_{\text{rel}} \leq 2,0\text{ dB}$	$B_{2,0\text{dB}}$	3,84	4,2	—	MHz
Amplitude ripple (p-p)	$\Delta\alpha$				
$f_N - 2,00\text{ MHz} \dots f_N + 2,00\text{ MHz}$		—	1,5	1,8	dB
$f_N - 1,92\text{ MHz} \dots f_N + 1,92\text{ MHz}$		—	0,9	1,5	dB
$f_N - 1,5\text{ MHz} \dots f_N + 1,5\text{ MHz}$		—	0,7	1,1	dB
Deviation of phase from linearity (rms)	$\Delta\varphi$				
$f_N - 1,92\text{ MHz} \dots f_N + 1,92\text{ MHz}$		—	1,5	2,0	°
Group delay deviation	ns				
$f_N - 1,92\text{ MHz} \dots f_N + 1,92\text{ MHz}$		—	110	150	
Relative attenuation (relative to α_{\min})	α_{rel}				
DC ... $f_N - 20,0\text{ MHz}$		45,0	50,0	—	dB
$f_N - 20,0\text{ MHz} \dots f_N - 10,0\text{ MHz}$		35,0	41,0	—	dB
$f_N - 10,0\text{ MHz} \dots f_N - 5,0\text{ MHz}$		30,0	34,0	—	dB
$f_N + 5,0\text{ MHz} \dots f_N + 10,0\text{ MHz}$		27,0	31,0	—	dB
$f_N + 10,0\text{ MHz} \dots f_N + 20,0\text{ MHz}$		32,0	36,0	—	dB
$f_N + 20,0\text{ MHz} \dots 350,0\text{ MHz}$		37,0	42,0	—	dB
Temperature coefficient of frequency²⁾	TC_f	—	-20	—	ppm/K

¹⁾ The specifications on this page hold for balanced / balanced operation (cf. test matching network 2 on p. 5). The specified minimum insertion attenuation does not include the losses in the transformers of the test circuit.

²⁾ Temperature dependence of f_c : $f_c(T) = f_c(T_0)(1 + TC_f(T - T_0))$



Data Sheet



Characteristics ¹⁾

Operating temperature range: $T = -20 \dots +85 \text{ }^\circ\text{C}$
 Terminating source impedance: $Z_S = 0,9 \text{ k}\Omega \parallel 60 \text{ nH}$
 Terminating load impedance: $Z_L = 1,1 \text{ k}\Omega \parallel 90 \text{ nH}$


		min.	typ.	max.	
Nominal frequency	f_N	—	190,0	—	MHz
Minimum insertion attenuation (including losses in matching circuit)	α_{\min}		8,8	9,8	dB
Passband width $\alpha_{\text{rel}} \leq 2,0 \text{ dB}$	$B_{2,2\text{dB}}$	3,84	4,2	—	MHz
Amplitude ripple (p-p)	$\Delta\alpha$				
$f_N - 2,00 \text{ MHz} \dots f_N + 2,00 \text{ MHz}$			1,5	2,4	
$f_N - 1,92 \text{ MHz} \dots f_N + 1,92 \text{ MHz}$		—	0,9	2,1	dB
$f_N - 1,5 \text{ MHz} \dots f_N + 1,5 \text{ MHz}$		—	0,7	1,1	dB
Deviation of phase from linearity (rms)	$\Delta\varphi$				
$f_N - 1,92 \text{ MHz} \dots f_N + 1,92 \text{ MHz}$		—	1,5	2,5	$^\circ$
Group delay deviation	ns				
$f_N - 1,92 \text{ MHz} \dots f_N + 1,92 \text{ MHz}$		—	110	180	
Relative attenuation (relative to α_{\min})	α_{rel}				
DC $\dots f_N - 20,0 \text{ MHz}$		45,0	50,0	—	dB
$f_N - 20,0 \text{ MHz} \dots f_N - 10,0 \text{ MHz}$		32,0	41,0	—	dB
$f_N - 10,0 \text{ MHz} \dots f_N - 5,0 \text{ MHz}$		28,0	34,0	—	dB
$f_N + 5,0 \text{ MHz} \dots f_N + 10,0 \text{ MHz}$		27,0	31,0	—	dB
$f_N + 10,0 \text{ MHz} \dots f_N + 20,0 \text{ MHz}$		30,5	36,0	—	dB
$f_N + 20,0 \text{ MHz} \dots 350 \text{ MHz}$		37,0	42,0	—	dB
Temperature coefficient of frequency²⁾	TC_f	—	-20	—	ppm/K

¹⁾ The specifications on this page hold for balanced / balanced operation (cf. test matching network 2 on p. 5). The specified minimum insertion attenuation does not include the losses in the transformers of the test circuit.

²⁾ Temperature dependence of f_c : $f_c(T) = f_c(T_0)(1 + TC_f(T - T_0))$




Test matching network 1 for unbalanced operation in 50-Ω environment (element values depend on PCB layout):



- Ls1 = 180 nH
- Lp2 = 100 nH
- Lp3 = 150 nH
- Ls4 = 200 nH
- Coils: Coilcraft 1008HQ


Test matching network 2 for balanced operation in 50-Ω environment (element values depend on PCB layout):




- Cs1 = Cs6 = 4.7 pF
- Cp2 = Cp5 = tbd
- Lp3 = 47 nH
- Lp4 = 68 nH
- Coils: Coilcraft 1008HQ
- Transformers: 1:4 Toko 616DB1004



Transfer function:



Transfer function and phase characteristics (pass band):





SAW Components

B7305

IF Filter for Mobile Communication

190 MHz

Data Sheet



Published by EPCOS AG

SAW MC WT, P.O. Box 80 17 09, 81617 Munich, GERMANY

☎ ++49 89 636 09, FAX (0 89) 636-2 26 89

© EPCOS AG 2002. Reproduction, publication and dissemination of this brochure and the information contained therein without EPCOS' prior express consent is prohibited.

Purchase orders are subject to the General Conditions for the Supply of Products and Services of the Electrical and Electronics Industry recommended by the ZVEI (German Electrical and Electronic Manufacturers' Association), unless otherwise agreed.

This brochure replaces the previous edition.

For questions on technology, prices and delivery please contact the Sales Offices of EPCOS AG or the international Representatives.

Due to technical requirements components may contain dangerous substances. For information on the type in question please also contact one of our Sales Offices.