



STEVAL-ISA001V1

6W dual output supply evaluation board using VIPer12A

Data Brief

Features

- Switch mode general purpose power supply
- Input: 85 to 264 VAC @ 50/60 Hz
- Output: 12V @ 0.5A
- Output power (peak) 6W
- Burst mode operation in standby for blue angel operation
- Current mode control
- Switching frequency 60 kHz
- Over 74% efficiency
- Auxiliary undervoltage lockout with hysteresis
- Output short circuit protection
- Thermal shutdown protection
- Meets EN55022 Class B EMI specification

Applications

This evaluation board is an off-line wide range dual output general-purpose power supply capable of delivering a total output power up to 6W. In low load condition, it operates in the automatic burst mode while in an overvoltage condition it will operate in hiccup mode. Other output voltages can easily be achieved by changing the transformer and a few components on the board, as shown in the application note. Transformers are readily available for the following configurations:

- 5V/12V
- 5V/15V
- 5V/24V



Description

The evaluation board consumes less than 1W total power consumption when working in the burst mode during standby operation and therefore, meets Blue Angel norm. Table 2 below outlines the total power consumption measured on the reference board at different line voltages with zero loads at both the outputs. The output voltages remain regulated when operating in burst mode condition.

1 General circuit description

The circuit operates from 85Vac to 264Vac input voltage with an output power peak of 6W through two output voltages of 5Vdc and 12Vdc. It contains an input fuse (F2), EMI filtering (C1, L1, and C2), and the secondary regulation is provided by U2 and U3, the optocoupler and TL431 respectively. For output filtering, the components used are the output capacitors C8 and C10. These two output capacitors are sized according to the ripple current and ripple voltage specifications. The two specifications determine the ESR and RMS current capabilities of the capacitors used. An additional LC (PI) filter is added to the 5Vdc output, C9-L2 configuration, for further effective ripple and noise rejection. The AC input is rectified and filtered by the bridge BR1 and the bulk capacitor C1 to generate the high voltage DC bus applied to the primary winding of the transformer, T1. The 5Vdc output is sensed with an optocoupler. It is possible to modify the output voltages by changing the transformer turns ratio and modifying the resistance values of R7 and R8 in the feedback loop. R2 and C4 form the snubber circuit needed to reduce the voltage ringing on the drain pin and the leakage spikes.

3 Revision history

Table 1. Document revision history

Date	Revision	Changes
20-Jul-2007	1	Initial release.

Please Read Carefully:

Information in this document is provided solely in connection with ST products. STMicroelectronics NV and its subsidiaries ("ST") reserve the right to make changes, corrections, modifications or improvements, to this document, and the products and services described herein at any time, without notice.

All ST products are sold pursuant to ST's terms and conditions of sale.

Purchasers are solely responsible for the choice, selection and use of the ST products and services described herein, and ST assumes no liability whatsoever relating to the choice, selection or use of the ST products and services described herein.

No license, express or implied, by estoppel or otherwise, to any intellectual property rights is granted under this document. If any part of this document refers to any third party products or services it shall not be deemed a license grant by ST for the use of such third party products or services, or any intellectual property contained therein or considered as a warranty covering the use in any manner whatsoever of such third party products or services or any intellectual property contained therein.

UNLESS OTHERWISE SET FORTH IN ST'S TERMS AND CONDITIONS OF SALE ST DISCLAIMS ANY EXPRESS OR IMPLIED WARRANTY WITH RESPECT TO THE USE AND/OR SALE OF ST PRODUCTS INCLUDING WITHOUT LIMITATION IMPLIED WARRANTIES OF MERCHANTABILITY, FITNESS FOR A PARTICULAR PURPOSE (AND THEIR EQUIVALENTS UNDER THE LAWS OF ANY JURISDICTION), OR INFRINGEMENT OF ANY PATENT, COPYRIGHT OR OTHER INTELLECTUAL PROPERTY RIGHT.

UNLESS EXPRESSLY APPROVED IN WRITING BY AN AUTHORIZED ST REPRESENTATIVE, ST PRODUCTS ARE NOT RECOMMENDED, AUTHORIZED OR WARRANTED FOR USE IN MILITARY, AIR CRAFT, SPACE, LIFE SAVING, OR LIFE SUSTAINING APPLICATIONS, NOR IN PRODUCTS OR SYSTEMS WHERE FAILURE OR MALFUNCTION MAY RESULT IN PERSONAL INJURY, DEATH, OR SEVERE PROPERTY OR ENVIRONMENTAL DAMAGE. ST PRODUCTS WHICH ARE NOT SPECIFIED AS "AUTOMOTIVE GRADE" MAY ONLY BE USED IN AUTOMOTIVE APPLICATIONS AT USER'S OWN RISK.

Resale of ST products with provisions different from the statements and/or technical features set forth in this document shall immediately void any warranty granted by ST for the ST product or service described herein and shall not create or extend in any manner whatsoever, any liability of ST.

ST and the ST logo are trademarks or registered trademarks of ST in various countries.

Information in this document supersedes and replaces all information previously supplied.

The ST logo is a registered trademark of STMicroelectronics. All other names are the property of their respective owners.

© 2007 STMicroelectronics - All rights reserved

STMicroelectronics group of companies

Australia - Belgium - Brazil - Canada - China - Czech Republic - Finland - France - Germany - Hong Kong - India - Israel - Italy - Japan - Malaysia - Malta - Morocco - Singapore - Spain - Sweden - Switzerland - United Kingdom - United States of America

www.st.com

