

Oxford Electrical Products Ltd

aud	0	0800 316 6060			
get an online quote	get a catalogue delivered	download entire catalogue	can't find what your looking for ??	back to catalogue index	home

PCB MOUNTING MINIATURE

A range of high quality, industry standard, audio frequency transformers, enclosed in ABS cases.

Specifically designed for direct printed circuit board mounting on a 0.1 inch grid. Each transformer is constructed with dual windings on the primary and secondary providing a wide range of impedance matching ratios to suit many input, interstage and output applications.

A foil screen is provided between the primary and secondary windings and the transformers are rated at 100mW at 300 Hz and 1mW at 30 Hz (less than 1% T.H.D.)


An optional Mu-metal screening can, is available if required. P/N A262CAN)



Transformer W28 H22 D23mm



Mumetal Can W29 H23 D24mm



Ratio	6.3+6.3:1+1		1+1:2+2		1+1:6.45+6.45	
Rallo	PRI	SEC	PRI	SEC	PRI	SEC
Part No.	A262A1E		A262A2E		A262A3E	
Impedance	150	3.75+	150+	600+	150+	6.25+
Individual windings	150 Ω	3.75 Ω	150Ω	600 Ω	150Ω	6.25k ^Ω
Series Connected	600 ^Ω C.T.	15 ^Ω C.T.	600 ^Ω C.T.	2.4kΩC.T.	600 ^Ω C.T.	25k ^Ω C.T.
Parallel Connected	150 Ω	3.75 Ω	150 Ω	600 Ω	150 Ω	6.25 \(\Omega\)
d c Resistance	10+10Ω	0.36+0.36 Ω	10+10Ω	55+55 Ω	9.6+9.6 □	535+605Ω
Frequency Range (+1.5db)	30Hz - 30kHz		30Hz - 35kHz		30Hz - 25kHz	
Proof test voltage : primary to secondary and windings to screen	1 kV		1 kV		1 kV	

Datio	1+1:1+1		1+1:1+1		
Ratio	PRI	SEC	PRI	SEC	
Part No.	A262	2A6E	A262A7E		
Impedance	150+	150+	600+	600+	
Individual windings	150Ω	150 Ω	600 Ω	600 Ω	
Series Connected	600 ^Ω C.T.	600ΩC.T.	2.4k ^Ω C.T.	2.4k ^Ω C.T.	
Parallel Connected	150Ω	150 Ω	600 Ω	600 Ω	
d c Resistance	15+15 ^Ω	20+20Ω	42+42 ^Ω	58+58 Ω	
Frequency Range (+1.5db)	30Hz - 30kHz		30Hz - 35kHz		
Proof test voltage : primary to secondary and windings to screen	1 kV		1 kV		

This range of transformers is also available with the Mu metal screening can fitted and may be ordered by replacing the suffix 'E' with the suffix 'C'