



Neon Circuit Component Lamps

Configuration	Part Number	Old Ref. Number	Design Current mA	Initial DC Breakdown Voltage	Initial DC Maintaining Voltage
Wire Terminal					
	2AA	NE-99	0.30	60-80	52-62
	2AC		1.50	125 Max.	-
	3AD	NE-98	0.30	65-80	Avg.>50
	3AG		0.40	60-90	Avg.>58
	3AG-B		0.40	65-73	52-62
	3AG-C		0.40	68-76	52-62
	3AG-F		0.40	65-73	64 Max.
	3AH		2.00	75-135	Avg.70
	3AJ		5.00	60-100	Avg.>59
	3AJ-C		5.00	60-100	Avg.>59
	4AD		0.50	105-135	60-80
	4AE		0.50	120-150	60-80
	5AB	NE-23	0.30	60-90	Avg.59
	5AB-A		0.30	60-80	50-65
	5AB-B		0.30	62-72	50-60
	5AB-BT		0.30	62-72	50-60
	5AB-T		0.30	60-90	Avg.59
	5AC	NE-68	0.30	60-90	52-65
	5AG	NE-81	0.10	64-80	50-58
	5AG-A	NE-76	0.40	68-76	50-60
	5AH	NE-83	5.00	60-100	Avg.>59
	5AH-A		5.00	60-85	50-65
	5AH-B		5.00	75-85	55-66
	5AH-D		3.00	60-85	50-70
	5AH-E		5.00	60-100	Avg.>61
	5AJ	NE-86	1.50	55-90	Avg.>57
	5AJ-A		1.50	55-75	45-65
	5AJ-B		1.50	70-90	55-75

147 Central Avenue
 Hackensack, NJ 07601
 Phone: (201) 489-8989
 Fax: (201) 489-6911

18703 Dix Toledo Road
 Brownstown, MI 48193

Saret Zone Franca, Edificio B
 Alajuela Costa Rica

E-mail: sales@chml.com • Web Site: www.chml.com

Chicago Miniature Lighting, LLC reserves the right to make specification revisions that enhance the design and/or performance of the product