
TOSHIBA Transistor Silicon NPN Epitaxial Type (PCT process) (Bias Resistor built-in Transistor)

RN1972FS,RN1973FS

Switching, Inverter Circuit, Interface Circuit and Driver Circuit Applications

- Two devices are incorporated into a fine pitch small mold (6-pin) package
- Incorporating a bias resistor into a transistor reduces parts count.
 Reducing the parts count enables the manufacture of ever more compact equipment and lowers assembly cost.
- Complementary to RN2972FS, RN2973FS

Equivalent Circuit and Bias Resistor Values




Maximum Ratings (Ta = 25°C) (Q1, Q2 common)


Characteristics	Symbol	Rating	Unit
Collector-base voltage	V_{CBO}	20	V
Collector-emitter voltage	V _{CEO}	20	٧
Emitter-base voltage	V _{EBO}	5	V
Collector current	I _C	50	mA
Collector power dissipation	P _C (Note)	50	mW
Junction temperature	Tj	150	°C
Storage temperature range	T _{stg}	-55~150	°C

Note: Total rating

Equivalent Circuit (top view)



Unit: mm



Weight: 0.001g (typ.)





Electrical Characteristics (Ta = 25°C) (Q1, Q2 common)


Characteristics		Symbol	Test Condition	Min	Тур.	Max	Unit
Collector cut-off curre	ent	I _{CBO}	$V_{CB} = 20 \text{ V}, I_{E} = 0$	_	_	100	nA
Emitter cut-off curren	t	I _{EBO}	$V_{EB} = 5 V, I_{C} = 0$	_	_	100	nA
DC current gain		h _{FE}	$V_{CE} = 5 \text{ V}, I_{C} = 1 \text{ mA}$	300	_	_	
Collector-emitter satu	ıration voltage	V _{CE (sat)}	$I_C = 5 \text{ mA}, I_B = 0.25 \text{ mA}$	_	_	0.15	V
Collector output capacitance		C _{ob}	$V_{CB} = 10 \text{ V}, I_{E} = 0, f = 1 \text{ MHz}$	_	1.2		pF
Input resistor	RN1972FS	R1	_	17.6	22	26.4	kΩ
	RN1973FS			37.6	47	56.4	


2

(Q1, Q2 common)













(Q1, Q2 common)










4



HANDLING PRECAUTION

When handling individual devices (which are not yet mounted on a circuit board), be sure that the environment is protected against electrostatic discharge. Operators should wear anti-static clothing, and containers and other objects that come into direct contact with devices should be made of anti-static materials.

RESTRICTIONS ON PRODUCT USE

030619EAA

- The information contained herein is subject to change without notice.
- The information contained herein is presented only as a guide for the applications of our products. No
 responsibility is assumed by TOSHIBA for any infringements of patents or other rights of the third parties which
 may result from its use. No license is granted by implication or otherwise under any patent or patent rights of
 TOSHIBA or others.
- TOSHIBA is continually working to improve the quality and reliability of its products. Nevertheless, semiconductor devices in general can malfunction or fail due to their inherent electrical sensitivity and vulnerability to physical stress. It is the responsibility of the buyer, when utilizing TOSHIBA products, to comply with the standards of safety in making a safe design for the entire system, and to avoid situations in which a malfunction or failure of such TOSHIBA products could cause loss of human life, bodily injury or damage to property.
 In developing your designs, please ensure that TOSHIBA products are used within specified operating ranges as set forth in the most recent TOSHIBA products specifications. Also, please keep in mind the precautions and conditions set forth in the "Handling Guide for Semiconductor Devices," or "TOSHIBA Semiconductor Reliability Handbook" etc..
- The TOSHIBA products listed in this document are intended for usage in general electronics applications (computer, personal equipment, office equipment, measuring equipment, industrial robotics, domestic appliances, etc.). These TOSHIBA products are neither intended nor warranted for usage in equipment that requires extraordinarily high quality and/or reliability or a malfunction or failure of which may cause loss of human life or bodily injury ("Unintended Usage"). Unintended Usage include atomic energy control instruments, airplane or spaceship instruments, transportation instruments, traffic signal instruments, combustion control instruments, medical instruments, all types of safety devices, etc.. Unintended Usage of TOSHIBA products listed in this document shall be made at the customer's own risk.
- TOSHIBA products should not be embedded to the downstream products which are prohibited to be produced and sold, under any law and regulations.