


SONET/SDH Dual Line Interface Transformer for E4/STM-1 Applications



- ☐ Compliant with ITU-T/G.703
- ☐ Supports 139.264 (E4) and 155.52 (STM-1) Mbps for Coded Mark Inversion (CMI) interfaces
- ☐ Designed to interface with Level One's LXT6155 for use with 75 Ω coaxial cable
- ☐ Dual design supports transmit and receive circuitry
- ☐ Designed for fast rise time and low signal distortion

Electrical Specifications @ 25°C — Operating Temperature -40°C to +85°C



Part Number	Turns Ratio (±5%)	Primary Inductance OCL (μH MIN) @ 20m Vrms, 100 kHz	Leakage Inductance L_L (nH MAX)	Interwinding Capacitance C_{ww} (pF MAX)	DC Resistance DCR (Ω MAX)	Hipot (Vrms MIN)
ST6200T	1 : 1	36.0	100	6.0	.30	1500

Note: Modules are packaged in tubes unless Tape & Reel packaging is specified. Add the suffix “-R” (such as ST6200T-R) for Tape & Reel orders. Tape & Reel parts can only be ordered in multiples of 1000 pieces.

Mechanical

Schematic

ST6200T



Dimensions: $\frac{\text{Inches}}{\text{mm}}$

Unless otherwise specified, all tolerances are $\pm \frac{.010}{0,25}$

Weight 1.0 grams (max)

Tape & Reel 1000/reel

Tube42/tube

U.S: 858 674 8100 • U.K: 44 1483 401 700 • France: 33 3 84 35 04 04 • Singapore: 65 287 8998 • Taiwan: 886 2 2698 0228 • <http://www.pulseeng.com>

PRELIMINARY A105.P (10/99)

SONET/SDH Dual Line Interface Transformer for E4/STM-1 Applications




Application Notes:

Pulse has designed the ST6200T, SONET/SDH dual line interface transformer specifically for high-speed, STM-1/E4 serial data interfaces utilizing 75 Ω coax cable. The isolation transformer protects the station from static charges that may develop on the cable and prevents ground loop currents from being transferred between stations. These devices have also been designed to provide inherent common rejection within the transmission pass band and thus reduce EMI. The high bandwidth of these devices minimizes data dependent jitter (DDJ) by providing fast signal rise times with minimal signal distortion. Insertion loss is typically less

than -3 dB within 10 MHz to 320 MHz passband and return loss is typically greater than -15 dB (8 MHz to 240 MHz) with 75 Ω load (this can be effected by circuit board layout and other external electrical parasitics). With traditional coaxial links, the transformer also provides a balanced differential to single-ended connection between the transmitter/receiver IC and the coax. The dual package allows connections of both transmit and receive channels as shown in the Application Circuit below. The auto-insertable SMD packaging allows for a cost-effective solution for the application.

Application Circuit:



NOTES:

1. Resistors R1, R2, R4, R5: 37.5 Ω , 2%, 1/4W
2. Resistors R3 and R6: 75 Ω , 2%, 1/4W

For More Information :

UNITED STATES (Worldwide)

12220 World Trade Drive
San Diego, CA 92128
Quick-Facts: 619 674 9672
<http://www.pulseeng.com>
TEL: 858 674 8100
FAX: 858 674 8262

UNITED KINGDOM (Northern Europe)

1 & 2 Huxley Road
The Surrey Research Park
Guildford, Surrey GU2 5RE
United Kingdom
TEL: 44 1483 401700
FAX: 44 1483 401701

FRANCE (Southern Europe)

Zone Industrielle
F-39270
Orgelet
France
TEL: 33 3 84 35 04 04
FAX: 33 3 84 25 46 41

SINGAPORE (Southern Asia)

150 Kampong Ampat
#07-01/02
KA Centre
Singapore 368324
TEL: 65 287 8998
FAX: 65 280 0080

TAIWAN, R.O.C. (Northern Asia)

3F-4, No. 81, Sec. 1
HsinTai Wu Road
Hsi-Chih, Taipei Hsien
Taiwan, R.O.C.
Tel: 886 2 2698 0228
FAX: 886 2 2698 0948

DISTRIBUTOR

Performance warranty of products offered on this data sheet is limited to the parameters specified. Data is subject to change without notice. Other brand and product names mentioned herein may be trademarks or registered trademarks of their respective owners.

♻️ Printed on recycled paper. ©1999, Pulse Engineering, Inc.

PRELIMINARY A105.P (10/99)