
General purpose (dual digital transistors) UMH8N / IMH8A

Features

 Two DTC114T chips in a EMT or UMT or SMT package.

Equivalent circuits



Package, marking, and packaging specifications


Туре	UMH8N	IMH8A	
Package	UMT6	SMT6	
Marking	H8	H8	
Code	TR	T108	
Basic ordering unit (pieces)	3000	3000	

● Absolute maximum ratings (Ta=25°C)

Parameter		Symbol	Limits	Unit
Collector-base voltage		Vсво	50	V
Collector-emitter voltage		Vceo	50	V
Emitter-base voltage		VEBO	5	V
Collector current		lc	100	mA
Power dissipation	UMH8N	Pd	150(TOTAL)	mW *1
	IMH8A	l Fu	300(TOTAL)	*2
Junction temperature		Tj	150	°C
Storage temperature		Tstg	-55 to +150	°C

^{*1 120}mW per element must not be exceeded.

●External dimensions (Unit:mm)



●Electrical characteristics (Ta=25°C)

Parameter	Symbol	Min.	Тур.	Max.	Unit	Conditions
Collector-base breakdown voltage	ВУсво	50	-	-	V	Ic=50μA
Collector-emitter breakdown voltage	BVceo	50	-	-	V	Ic=1mA
Emitter-base breakdown voltage	BVEBO	5	-	-	V	Iε=50μA
Collector cutoff current	Ісво	-	-	0.5	μΑ	Vcb=50V
Emitter cutoff current	IEBO	-	-	0.5	μА	V _{EB} =4V
Collector-emitter saturation voltage	VcE(sat)	-	-	0.3	V	Ic/I _B =10mA/1mA
DC current transfer ratio	hre	100	250	600	_	VcE=5V, Ic=1mA
Transition frequency	fτ	-	250	-	MHz	VcE=10V, IE= -5mA, f=100MHz *
Input resistance	R ₁	7	10	13	kΩ	-

^{*}Transition frequency of the device.

•Electrical characteristics curves




Fig.1 DC current gain vs. collector current




Fig.2 Collector-emitter saturation voltage vs. collector current

ROHM

Notes

- No technical content pages of this document may be reproduced in any form or transmitted by any means without prior permission of ROHM CO.,LTD.
- The contents described herein are subject to change without notice. The specifications for the
 product described in this document are for reference only. Upon actual use, therefore, please request
 that specifications to be separately delivered.
- Application circuit diagrams and circuit constants contained herein are shown as examples of standard
 use and operation. Please pay careful attention to the peripheral conditions when designing circuits
 and deciding upon circuit constants in the set.
- Any data, including, but not limited to application circuit diagrams information, described herein are intended only as illustrations of such devices and not as the specifications for such devices. ROHM CO.,LTD. disclaims any warranty that any use of such devices shall be free from infringement of any third party's intellectual property rights or other proprietary rights, and further, assumes no liability of whatsoever nature in the event of any such infringement, or arising from or connected with or related to the use of such devices.
- Upon the sale of any such devices, other than for buyer's right to use such devices itself, resell or
 otherwise dispose of the same, no express or implied right or license to practice or commercially
 exploit any intellectual property rights or other proprietary rights owned or controlled by
- ROHM CO., LTD. is granted to any such buyer.
- Products listed in this document are no antiradiation design.

The products listed in this document are designed to be used with ordinary electronic equipment or devices (such as audio visual equipment, office-automation equipment, communications devices, electrical appliances and electronic toys).

Should you intend to use these products with equipment or devices which require an extremely high level of reliability and the malfunction of with would directly endanger human life (such as medical instruments, transportation equipment, aerospace machinery, nuclear-reactor controllers, fuel controllers and other safety devices), please be sure to consult with our sales representative in advance.

About Export Control Order in Japan

Products described herein are the objects of controlled goods in Annex 1 (Item 16) of Export Trade Control Order in Japan.

In case of export from Japan, please confirm if it applies to "objective" criteria or an "informed" (by MITI clause) on the basis of "catch all controls for Non-Proliferation of Weapons of Mass Destruction.

ROHM

Appendix1-Rev1.1