# Millenium 3











#### Millenium 3 logic controllers



Туре		Part number	Power supply	Inputs	Outputs
With display					
on property	CD12	88970041	24 V	8 digital (of which 4 are analogue)	4 x 8 A relays
THE REAL PROPERTY.		88970042	24 V	8 digital (of which 4 are analogue)	4 solid state 0.5 A (of which 1 is PWM)
60 NO NO NO		88970043	100 → 240 V ~	8 digital	4 x 8 A relays
		88970044	24 V $\sim$	8 digital	4 x 8 A relays
		88970045	12 V	8 digital (of which 4 are analogue)	4 x 8 A relays
.m	CD20	88970051	24 V	12 digital (of which 6 are analogue)	8 x 8 A relays
THE REAL PROPERTY.		88970052	24 V	12 digital (of which 6 are analogue)	8 solid state 0.5 A (of which 4 are PWM)
NAME OF TAXABLE PARTY.		88970053	100 → 240 V ~	12 digital	8 x 8 A relays
		88970054	24 V $\sim$	12 digital	8 x 8 A relays
		88970055	12 V	12 digital (of which 6 are analogue)	8 x 8 A relays
Without display					
as sections	CB12	88970021	24 V	8 digital (of which 4 are analogue)	4 x 8 A relays
A		88970023	100 → 240 V ~	8 digital	4 x 8 A relays
		88970024	24 V $\sim$	8 digital	4 x 8 A relays
		88970840 <b>NEW</b>	12 V	8 digital (of which 4 are analogue)	4 solid state 0.5 A (of which 1 is PWM)
as succession.	CB20	88970031	24 V	12 digital (of which 6 are analogue)	8 x 8 A relays
F		88970033	100 → 240 V ~	12 digital	8 x 8 A relays
		88970034	24 V $\sim$	12 digital	8 x 8 A relays



#### ■ Ergonomic display



■ Optimum memory capacity

#### Millenium 3 logic controllers operate with the following software:



#### ■ M3 SOFT

Multilingual programming software (CD-ROM) including a library of specific functions.
Part no.: 88970111

#### ■ M3 ALARM

Alarm management software (CD-ROM)

Part no.: 88970116

This software is used alongside the M3MOD communication interface

(part no.: 88970117).

For all details of hardware adaptation, see pages 64-65.



www.millenium3.crouzet.com

# "Compact" range selection guide

Modem communication solutions			Modular power supplies (1)					Starter kits and demo case
МЗМОД	STN	GSM	12 V DC - 24 W	44.05	24 V DC - 15 W	24 V DC - 30 W	24 V DC - 60 W	
88970117	88970118	88970119	88950306	88950303	88950304	88950307	88950302	Standard
				•		-	-	88970080
•				-		•		88970106 (case)
•								88970081
			•					
•				<b>=</b>	•			88970082
•				•		•	<b>=</b>	
•								88970083
•								
•			•					
				•	•	•		
•								
•			•					
•				-		•	•	
•								
•								

Compatible □ Mounted with the M3MOD:

- STN modem, or GSM modem

<sup>(1)</sup> Find the whole "Power Supplies" offer on pages 58-59.



#### The 4 starter kits each contain:

■ 1 CD12 or CD20 logic controller + 1 USB link cable + 1 M3 SOFT programming software application (CD-ROM) including a library of specific functions.

Part no.: 88970080 / 88970081 / 88970082 / 88970083



#### The demonstration case contains:

■ 1 CD12 logic controller + 1 USB link cable + 1 M3 SOFT programming software application (CD-ROM) including the library of specific functions + 1 voltage adaptor + 1 I/O simulation card.

Part no.: 88970106



# → "Compact" range with display

- Budget solution with display
- Memory: 120 lines in LADDER language and up to 350 "typical" blocks in FBD language
- LCD with 4 lines of 18 characters and configurable backlighting
- Selective parameter setting: You can choose the parameters that can be adjusted on the front panel
- Analogue inputs 0-10 V or 0-20 mA/Pt 100 with converters (see page 50)





CD20


Part nui	mbers			
Туре	Input	Output	Supply	Code
CD12	8 digital (including 4 analogue)	4 relays 8 A	24 V ===	88970041
	8 digital (including 4 analogue)	4 solid state 0.5 A (including 1 PWM)	24 V ===	88970042
	8 digital	4 relays 8 A	100 → 240 V ~	88970043
	8 digital	4 relays 8 A	24 V $\sim$	88970044
	8 digital (including 4 analogue)	4 relays 8 A	12 V <del></del>	88970045
CD20	12 digital (including 6 analogue)	8 relays 8 A	24 V ===	88970051
	12 digital (including 6 analogue)	8 solid state 0.5 A (including 4 PWM)	24 V ===	88970052
	12 digital	8 relays 8 A	100 → 240 V ~	88970053
	12 digital	8 relays 8 A	24 V $\sim$	88970054
	12 digital (including 6 analogue)	8 relays 8 A	12 V	88970055


# Type Description Code M3 SOFT Multilingual programming software containing specific library functions (CD-ROM) 88970111 PA EEPROM memory cartridge 88970108 3 m serial link cable: PC → Millenium 3 88970102 3 m USB link cable: PC → Millenium 3 88970109 Millenium 3 → Bluetooth interface (class A 10 m) 88970104

Starter I	Starter kits (see page 27 for details)							
Туре	Input	Output	Supply	Code				
Kit 12	8 digital (including 4 analogue)	4 relays	24 V ===	88970080				
	8 digital	4 relays	100 → 240 V ~	88970081				
Kit 20	12 digital (including 6 analogue)	8 relays	24 V ===	88970082				
	12 digital	8 relays	100 → 240 V ~	88970083				

#### Dimensions (mm)







#### **Input / Output Connections**

See Page 40-43 for details or to find instruction sheets visit: www.millenium3.crouzet.com in "Download"



# → "Compact" range without display

- Simply a control system solution inside a modular casing
- Memory: 120 lines in LADDER language and up to 350 "typical" blocks in FBD language
- No display or parameter-setting buttons to avoid tampering by unauthorised users
- Analogue inputs 0-10 V— or 0-20 mA/Pt 100 with converters (see page 50)





**CB12** 

		CB
		OL


Part nui	Part numbers								
Туре	Input	Output	Supply	Code					
CB12	8 digital (including 4 analogue)	4 relays 8 A	24 V	88970021					
	8 digital	4 relays 8 A	100 → 240 V ~	88970023					
	8 digital	4 relays 8 A	24 V $\sim$	88970024					
	8 digital (including 4 analogue)	4 solid state 0.5 A (including 1 PWM)	12 V ===	88970840					
CB20	12 digital (including 6 analogue)	8 relays 8 A	24 V ===	88970031					
	12 digital	8 relays 8 A	100 → 240 V ~	88970033					
	12 digital	8 relays 8 A	24 V ∼	88970034					


#### **Accessories**

Туре	Description	Code
M3 SOFT	Multilingual programming software containing specific library functions (CD-ROM)	88970111
PA	EEPROM memory cartridge	88970108
	3 m serial link cable: PC → Millenium 3	88970102
	3 m USB link cable: PC → Millenium 3	88970109
	Millenium 3 → Bluetooth interface (class A 10 m)	88970104

#### Dimensions (mm)







#### **Input / Output Connections**

See Page 40-43 for details or to find instruction sheets visit: www.millenium3.crouzet.com in "Download"





#### Millenium 3 logic controllers



Туре	Part number		Power supply	Inputs	Outputs
	With XD10/ XD26 display	Without display XB10/XB26			
to make you process	88970141	88970131 <b>NEW</b>	24 V <del></del>	6 digital (of which 4 are analogue)	4 x 8 A relays
	88970142	88970132 <b>NEW</b>	24 V <del></del>	6 digital (of which 4 are analogue)	4 solid state 0.5 A (of which 1 is PWM)
d to be set	88970143	88970133 <b>NEW</b>	100 → 240 V ~	6 digital	4 x 8 A relays
	88970144	88970134 <b>NEW</b>	24 V $\sim$	6 digital	4 x 8 A relays
A	88970161	88970151 <b>NEW</b>	24 V <del></del>	16 digital (of which 6 are analogue)	10 relays, of which 8 are 8 A and 2 are 5 A
	88970162	88970152 <b>NEW</b>	24 V <del></del>	16 digital (of which 6 are analogue)	10 solid state 0.5 A (of which 4 are PWM)
of the state of the	88970163	88970153 <b>NEW</b>	100 → 240 V ~	16 digital	10 relays, of which 8 are 8 A and 2 are 5 A
	88970164	88970154 <b>NEW</b>	24 V $\sim$	16 digital	10 relays, of which 8 are 8 A and 2 are 5 A
	88970165	88970155 <b>NEW</b>	12 V	16 digital (of which 6 are analogue)	10 relays, of which 8 are 8 A and 2 are 5 A
	88970814NEW	-	12 V	16 digital (of which 6 are analogue)	10 solid state 0.5 A (of which 4 are PWM)

Extensions '	Extensions "Sandwich"								
Туре		Part number	Power supply	Inputs	Outputs				
TOR									
********	XE10	88970321	Via the 24 V controller	6 digital	4x5A relays, 1 of which is a changeover relay				
		88970323	100 → 240 V ~	6 digital	4 x 5 A relays, 1 of which is a changeover relay				
		88970324	24 V $\sim$	6 digital	4 x 5 A relays, 1 of which is a changeover relay				
Туре		Part number	Power supply	Mains	Characteristics of exchanges (words)				
Communication									
m 10	XN05	88970270	Via the 24 V === controller	Modbus TCP Ethernet protocol	Read: 8 - Read/Write: 8 Clock: 4 - Status: 1				
	XN03	88970250	Via the 24 V controller	Modbus RS-485 (slave)	Read: 8 - Read/Write: 8 Clock: 4 - Status: 1				
	XN06	88972250 NEW	Via the 24 V == controller	Modbus RS-485 (slave)	Read: 8 - Read/Write: 8 Clock: 4 - Status: 1				



#### Millenium 3 logic controllers operate with the following software:

#### ■ M3 SOFT

Multilingual programming software (CD-ROM) including the library of specific functions.

Part no.: 88970111

#### ■ M3 ALARM

Alarm management software (CD-ROM)

Part no.: 88970116

This software is used alongside the M3MOD communication

interface (part no.: 88970117).

For all details of hardware adaptation, see pages 64-65.



www.millenium3.crouzet.com

# "Expandable" range selection guide

Modem communication solutions			Modular power supplies (1)				Starter kits	
МЗМОО	STN	GSM	12 V DC - 24 W	24 V DC - 7.5 W	24 V DC - 15 W	24 V DC - 30 W	24 V DC - 60 W	
88970117	88970118	88970119	88950306	88950303	88950304	88950307	88950302	Expandable
				•	•	•	•	
•				•	•	•	•	
•								
•								
•	0			•	•		•	88970084
•				•	•	•	•	
•								88970085
•								
•			•					
•			•					

(1) Find the whole "Power Supplies" offer on pages 58-59.

- Compatible □ Mounted with the M3MOD:
- STN modem, or GSM modem

Termination extensions							
Туре		Part number	Power supply	Inputs	Outputs		
Digital							
and the second	XR06	88970211	Via the 24 V controller	4 digital	2 x 8 A relays		
		88970213	Via the 100 $\Rightarrow$ 240 V $\sim$ controller	4 digital	2 x 8 A relays		
		88970214	Via the 24 V $\sim$ controller	4 digital	2 x 8 A relays		
		88970215	Via the 12 V == controller	4 digital	2 x 8 A relays		
-	XR10	88970221	Via the 24 V == controller	6 digital	4 x 8 A relays		
		88970223	Via the 100 → 240 V $\sim$ controller	6 digital	4 x 8 A relays		
		88970224	Via the 24 V $\sim$ controller	6 digital	4 x 8 A relays		
		88970225	Via the 12 V == controller	6 digital	4 x 8 A relays		
-	XR14	88970231	Via the 24 V == controller	8 digital	6 relays, of which 4 are 8 A and 2 are 5 A		
		88970233	Via the 100 → 240 V $\sim$ controller	8 digital	6 relays, of which 4 are 8 A and 2 are 5 A		
Tarana a		88970234	Via the 24 V $\sim$ controller	8 digital	6 relays, of which 4 are 8 A and 2 are 5 A		
		88970235	Via the 12 V == controller	8 digital	6 relays, of which 4 are 8 A and 2 are 5 A		
Analogue							
	XA04	88970241	Via the 24 V controller	1 analogue (0-10 V/0-20 mA), 1 analogue (0-10 V/0-20 mA/Pt100)	2 analogue (0-10 v)/PWM		



#### The 2 starter kits each contain:

- 1 XD26 logic controller + 1 USB link cable +
- 1 M3 SOFT programming software application (CD-ROM) including a library of specific functions.

Part no.: 88970084 / 88970085



## → "Expandable" range with display

- "High-performance" expandable solution with display
- Extended memory: 120 lines in LADDER language and up to 700 "typical" blocks in FBD language
- LCD with 4 lines of 18 characters and configurable backlighting
- Selective parameter setting: You can choose the parameters that can be adjusted on the front panel
- Analogue inputs 0-10 V or 0-20 mA/Pt 100 with converters (see page 50)
- Open to XN network communication extensions and digital I/O or analogue extensions






Part nun	nbers			
Туре	Input	Output	Supply	Code
XD10	6 digital (including 4 analogue)	4 relays 8 A	24 V ===	88970141
	6 digital (including 4 analogue)	4 solid state 0.5 A (including 1 PWM)	24 V ===	88970142
	6 digital	4 relays 8 A	100 → 240 V ~	88970143
	6 digital	4 relays 8 A	24 V $\sim$	88970144
XD26	16 digital (including 6 analogue)	10 relays (8 x 8 A relay and 2 x 5 A relay)	24 V ===	88970161
	16 digital (including 6 analogue)	10 solid state 0.5 A (including 4 PWM)	24 V ===	88970162
	16 digital	10 relays (8 x 8 A relay and 2 x 5 A relay)	100 → 240 V ~	88970163
	16 digital	10 relays (8 x 8 A relay and 2 x 5 A relay)	24 V ∼	88970164
	16 digital (including 6 analogue)	10 relays (8 x 8 A relay and 2 x 5 A relay)	12 V ===	88970165
	16 digital (including 6 analogue)	10 solid state 0.5 A (including 4 PWM)	12 V	88970814


Accessor	ries	
Туре	Description	Code
M3 SOFT	Multilingual programming software containing specific library functions (CD-ROM)	88970111
PA	EEPROM memory cartridge	88970108
	3 m serial link cable: PC → Millenium 3	88970102
	3 m USB link cable: PC → Millenium 3	88970109
	Millenium 3 → Bluetooth interface (class A 10 m)	88970104

Starter R	itis (see page 31 for details)			
Туре	Input	Output	Supply	Code
Kit 26	16 digital (including 6 analogue)	10 relays (8 x 8 A relay and 2 x 5 A relay)	24 V	88970084
	16 digital	10 relays (8 x 8 A relay and 2 x 5 A relay)	100 → 240 V ~	88970085

#### **Dimensions (mm)**



Startor kite (ego page 31 for details)



#### **Input / Output Connections**

See Page 40-43 for details or to find instruction sheets visit: www.millenium3.crouzet.com in "Download"



# → "Expandable" range without display

- "High-performance" expandable solution without display
- Extended memory: 120 lines in LADDER language and up to 700 "typical" blocks in FBD language
- No display or parameter-setting buttons to avoid tampering by unauthorised users
- Analogue inputs 0-10 V == or 0-20 mA/Pt 100 with converters (see page 50)
- Open to XN network communication extensions and digital I/O or analogue extensions





XB10

XB26

Туре	Input	Output	Supply	Code
XB10	6 digital (including 4 analogue)	4 relays 8 A	24 V ===	88970131*
	6 digital (including 4 analogue)	4 solid state 0.5 A (including 1 PWM)	24 V ===	88970132
	6 digital	4 relays 8 A	100 → 240 V ~	88970133*
	6 digital	4 relays 8 A	24 V $\sim$	88970134
XB26	16 digital (including 6 analogue)	10 relays (8 x 8 A relay and 2 x 5 A relay)	24 V ===	88970151
	16 digital (including 6 analogue)	10 solid state 0.5 A (including 4 PWM)	24 V ===	88970152
	16 digital	10 relays (8 x 8 A relay and 2 x 5 A relay)	100 → 240 V ~	88970153
	16 digital	10 relays (8 x 8 A relay and 2 x 5 A relay)	24 V $\sim$	88970154
	16 digital (including 6 analogue)	10 relays (8 x 8 A relay and 2 x 5 A relay)	12 V	88970155

<sup>\*</sup>Available 2<sup>nd</sup> quarter of 2008

#### General characteristics


See page 22, except:


Certifications	UL, CSA	

#### Accessories

Type	Description	Code
M3 SOFT	Multilingual programming software containing specific library functions (CD-ROM)	88970111
PA	EEPROM memory cartridge	88970108
PA	3 m serial link cable: PC → Millenium 3	88970102
PA	3 m USB link cable: PC → Millenium 3	88970109
PA	Millenium 3 → Bluetooth interface (class A 10 m)	88970104

#### Dimensions (mm)





#### **Input / Output Connections**

See Page 40-43 for details or to find instruction sheets visit: www.millenium3.crouzet.com in "Download"



## → Sandwich communication extensions for XD10/XB10 & XD26/XB26

- Exchange of input/output state or of internal values via communication networks
- Power supply via the controller







Part numbers				
Туре	Description	Supply	Code	
XN03	Modbus RS-485 slave communication extension 4 words	Via the 24 V == controller	88970250	
XN06	Modbus RS-485 slave communication extension 8 words	Via the 24 V == controller	88972250	
XN05	Ethernet protocol TCP Modbus extension	Via the 24 V == controller	88970270	


General characteristics	88970250 & 88972250	88970270
See page 22, except:		
Certifications	UL, CSA, GL (UL, CSA: 88972250)	UL, CSA GL pending
Earthing	Yes, refer to the quick reference guide supplied with the product	Yes, refer to the quick reference guide supplied with the product
Operating temperature	-20 → +55°C (+40°C in a non-ventilated enclosure) in accordance with IEC/EN 60068- 2-1 and IEC/EN 60068-2-2	0 → +55°C (+40°C in a non-ventilated enclosure) in accordance with IEC 60068-2- and IEC 60068-2-2
Cable length	Maximum length of the network: 1000 m (9600 Baud max, AWG26)	Maximum length between 2 controllers: 100 n

Communication parameters	88970250 & 88972250	88970270	
Type of link	2 or 4-wire; RTU or ASCII	-	
Transmission rate (Bauds)	1200, 2400, 4800, 9600, 19200, 28800,	38400, -	
	57600		
Parity	None; even; odd	-	
Addressing	1 →247	Static or dynamic	

Characteristics of exchanges	88970250	88972250	88970270	
Programming with Ladder language				
Image of smart relay I/O	4	4	-	
Status	1	1	-	
Programming with FBD language	4	8	8	
Read/Write	4	8	8	
Clock words	4	12	4	
Status words	1	1	1	

#### **Dimensions (mm)**

#### XN03 - XN05 - XN06





# → Digital sandwich extension for XD10/XB10 and XD26/XB26


- Can be used to reach up to 50 inputs/outputs in conjunction with XR14 termination extensions
- Relay outputs one of which is a changeover relay



Part nu	mbers		
Туре	Input	Output Supply	Code
XE10	6 digital	4 relays 5 A (1 of which is a changeover relay) Via the 24 V controller	88970321
	6 digital	4 relays 5 A (1 of which is a changeover relay) $100 \rightarrow 240 \text{ V} \sim$	88970323
	6 digital	4 relays 5 A (1 of which is a changeover relay) $$ 24 V $\sim$	88970324

#### **Dimensions (mm)**

#### XE10



#### Input / Output Connections

See Page 40-43 for details or to find instruction sheets visit: www.millenium3.crouzet.com in "Download"



## → Digital extension for XD10/XB10 and XD26/XB26

- Power supply via the controller at the same voltage as the inputs
- Number of inputs/outputs can be configured in accordance with your requirements









Туре	Input	Output	Supply	Code
XR06	4 digital	2 relays 8 A	Via the 24 V == controller	88970211
	4 digital	2 relays 8 A	Via the 100 → 240 V ~ controller	88970213
	4 digital	2 relays 8 A	Via the 24 V $\sim$ controller	88970214
	4 digital	2 relays 8 A	Via the 12 V == controller	88970215
XR10	6 digital	4 relays 8 A	Via the 24 V == controller	88970221
	6 digital	4 relays 8 A	Via the 100 → 240 V ~ controller	88970223
	6 digital	4 relays 8 A	Via the 24 V $\sim$ controller	88970224
	6 digital	4 relays 8 A	Via the 12 V == controller	88970225
XR14	8 digital	6 relays (4 x 8 A relay and 2 x 5 A relay)	Via the 24 V == controller	88970231
	8 digital	6 relays (4 x 8 A relay and 2 x 5 A relay)	Via the 100 →240 V ~ controller	88970233
	8 digital	6 relays (4 x 8 A relay and 2 x 5 A relay)	Via the 24 V $\sim$ controller	88970234
	8 digital	6 relays (4 x 8 A relay and 2 x 5 A relay)	Via the 12 V === controller	88970235

#### Dimensions (mm)





#### **Input / Output Connections**

See Page 40-43 for details or to find instruction sheets visit: www.millenium3.crouzet.com in "Download"

# → Analogue extension for XD10/XB10 and XD26/XB26

- Direct connection of analogue 0-10 V or 0-20 mA or Pt 100 inputs (10 bits) can be configured using the M3
- 2 analogue 0-10 V or PWM outputs (10 bits) can be configured using the M3 SOFT software
- Ramp can be parameterised for outputs used as 0-10 V outputs
- Power supply via the controller



XA04

Part nu	Part numbers					
Type	Input	Output	Supply	Code		
XA04	1 analogue (0-10 V / 0-20 mA), 1 analogue (0-10 V / 0-20 mA / Pt100)	2 analogue (0-10 V) / PWM	Via the 24 V == controller	88970241		



#### Characteristics of analogue extension 88970241

#### General characteristics of analogue extension 88970241

See page 22, except: Certifications

UL, CSA

GL (pending)
Yes, refer to the quick reference guide supplied with the product Earthing

Analogue inputs			
Inputs used as analogue inputs	0-10 V	0-20 mA	Pt 100
Input	IP and IQ	IP and IQ	IQ
Input range	0 → 10 V ===	0 → 20 mA	-25 → 125°C
Input impedance	≥ 18 kΩ	246 Ω	-
Maximum non destructive current/voltage	30 V	30 mA	-
Value of LSB	9.8 mV	20 μΑ	0.15°C
Input type	Common mode	Common mode	Pt 100 probe - IEC 751 - 3-wire
Resolution	10 bits	10 bits	10 bits
Conversion time	Module cycle time	Module cycle time	Module cycle time
Accuracy at 25°C	± 1%	± 1%	±1.5°C
Accuracy at 55°C	± 1%	± 1%	±1.5°C
Isolation between analogue channel and power	None	None	None
supply			
Longueur câble	10 m maximum, with shielded	10 m maximum, with shielded	10 m maximum, with shielded
	cable (sensor not isolated)	cable (sensor not isolated)	cable (sensor not isolated)
Protection against polarity inversions	Command ignored	Command ignored	Command ignored


Analogue outputs	
Range output	0 → 10 V
Input type	Resistive
Max. load	10 mA
Value of LSB	10 mV
Resolution	10 bits
Conversion time	Controller cycle time
Accuracy at 25°C	±1% of full scale
Accuracy at 55°C	±1% of full scale
Repeat accuracy at 55 °C	± 1%
Isolation between analogue channel and power	None
supply	
Cable length	10 metres maximum, with shielded cable (sensor not isolated)
Protection against polarity inversions	Yes

P	w	M
	w	ш

Range output	V power supply
Max. load	$\geq$ 1.2 k $\Omega$ (I $\leq$ 20 mA)
PWM cyclic ratio	1024 steps
Frequency	78 Hz, 312.5 Hz, 666.6 Hz, 1000 Hz, 1250 Hz, 1428 Hz, 1666 Hz, 2000 Hz
Accuracy	1% across the entire temperature range for PWM ratios from 5% to 95%
Built-in protections	Against overvoltages: Yes

### Dimensions (mm)

#### **XA04**



#### **Input / Output Connections**

See Page 40-43 for details or to find instruction sheets visit: www.millenium3.crouzet.com in "Download"



# → Modem communication plug and play solutions

- For remote control of your application
- Automatic notification of alarms via SMS (GSM Modem) / email or on a PC with M3 ALARM software.
- Millenium 3 program can be downloaded, modified and sent
- Input and output states, as well as all program values, can be polled and controlled remotely
- 2 types of pre-configured ready-to-use modem:
  - STN modem for wired transmission networks
  - GSM modem for wireless communication







M3MOD STN GSM

Part numbers			
Туре	Description	Supply	Code
M3MOD	Modem communication interface	12-24 V	88970117
STN	STN modem	12-24 V ===	88970118
GSM	GSM modem 850/900/1800/1900 MHz	12-24 V <del></del>	88970119

Accessories		
Туре	Description	Code
PA	1.80 m serial link cable: DB9/DB9	88970123
M3 ALARM	Alarm management software (CD-ROM)	88970116

#### **Characteristics of the communication Modem system**

General characteristics of the modem communication	88970117	88970118	88970119
See page 22, except:			
Certifications	UL, CSA	UL, CSA	UL, CSA, CE, FCC, IC, PTCRB_B&TTF

Power supply	88970117	88970118	88970119
Nominal voltage (V)	12 → 24 V <del></del>	12 → 24 V <del></del>	12 → 24 V <del></del>
Operating limits	-13% / + 20%	-13% / + 5%	-54% / + 33%
	or 10 → 28.8 V ===	or 10 → 30 V ===	or 5.5 → 32 V ===
Ripple	5% max.	-	-
Nominal current under 12 V DC	30 mA	140 mA	165 mA
Nominal current under 24 V DC	30 mA	70 mA	87 mA
Peak current on energisation	550 mA	9600 mA	2100 mA at 5.5 V
Max. absorbed power	1.1 W	-	2.1 W
Immunity from micro power cuts	1 ms, repetition 20 times	No	-
Protection against polarity inversions	Yes	-	No
Fuse protection	1 A fuse	-	With fuse 2.5 A

Characteristics of the "COM-M3" link with the controller	
Type of connector	Specific Millenium
Type of link	Specific Millenium communication protocol
Compatibility	Only with Millenium controllers version ≥ V2.1
Isolation of "Com-M3" connector from the "Com-M" connector	Via optocoupler ∼ 1780 V
Isolation of "Com-M3" connector from the ± supply terminals	Via optocoupler $\sim$ 1780 V
Characteristics of the "COM M2" link with the modern	

Characteristics of the "COM-M3" link with the modem	
Type of connector	Specific Millenium
Type of link with Modem connector cable	RS 232 serial (supplied with the communication interface)
Compatibility	Only with Millenium controllers version ≥ V2.1
Analogue RTC modem compatibility	AT commands
GSM modem compatibility	AT commands
Isolation of "Com-M" connector from the Modem	Via link cable to Modem (supplied)
Isolation of "Com-M" connector from the ± supply terminals	Via link cable to Modem (supplied)

