


INA22 is a 2-input NAND gate with one inverted input 2x drive strength.

Truth Table

A	B	Q
0	1	0
X	0	1
1	X	1


Capacitance

Pin	Cap [pF]
A	0.008
B	0.018

Area

0.141 mils²
91 μ m²

Power

0.832 μ W/MHz

Delay [ns] = tpd.. = f(SL, L)

Output Slope [ns] = op_sl.. = f(SL, L)

with SL = Input Slope [ns] ; L = Output Load [pF]

with L = Output Load [pF]

AC Characteristics: Tj = 25°C VDD = 3.3V Typical Process

AC Characteristics

Slope [ns]	Rise				Fall			
	0.1		2		0.1		2	
Load [pF]	0.03	0.3	0.03	0.3	0.03	0.3	0.03	0.3
Delay A => Q	0.25	0.71	0.5	0.95	0.23	0.63	0.42	0.82
Delay B => Q	0.11	0.57	0.35	0.87	0.11	0.49	0.15	0.68
Slew A => Q	0.31	1.81	0.35	1.82	0.22	1.1	0.29	1.12
Slew B => Q	0.32	1.84	0.73	2.07	0.18	1.08	0.6	1.38