


SWITCHING APPLICATION.

INTERFACE CIRCUIT AND DRIVER CIRCUIT APPLICATION

FEATURES


- With Built-in Bias Resistors.
- Simplify Circuit Design.
- Reduce a Quantity of Parts and Manufacturing Process.

EQUIVALENT CIRCUIT



BIAS RESISTOR VALUES

TYPE NO.	R1(kΩ)	R2(kΩ)
KRA116S	1	10
KRA117S	2.2	2.2
KRA118S	2.2	10
KRA119S	4.7	10
KRA120S	10	4.7
KRA121S	47	10
KRA122S	100	100




MAXIMUM RATING (Ta=25°C)

CHARACTERISTIC		SYMBOL	RATING	UNIT
Output Voltage	KRA116S~122S	V _O	-50	V
	KRA116S		-10, 5	
	KRA117S		-12, 10	
	KRA118S		-12, 5	
	KRA119S		-20, 7	
	KRA120S		-30, 10	
	KRA121S		-40, 15	
Input Voltage	KRA122S	V _I	-40, 10	V
Output Current	KRA116S~122S	I _O	-100	mA
Power Dissipation		P _D	200	mW
Junction Temperature		T _j	150	°C
Storage Temperature Range		T _{stg}	-55~150	°C

MARK SPEC

TYPE	KRA116S	KRA117S	KRA118S	KRA119S	KRA120S	KRA121S	KRA122S
MARK	P2	P4	P5	P6	P7	P8	P9

Marking



KRA116S ~ KRA122S

ELECTRICAL CHARACTERISTICS (Ta=25°C)

CHARACTERISTIC		SYMBOL	TEST CONDITION	MIN.	TYP.	MAX.	UNIT
Output Cut-off Current	KRA116S ~ 122S	I _{O(OFF)}	V _O =-50V, V _I =0	-	-	-500	nA
DC Current Gain	KRA116S	G _I	V _O =-5V, I _O =-5mA	33	-	-	
	KRA117S		V _O =-5V, I _O =-20mA	20	-	-	
	KRA118S		V _O =-5V, I _O =-10mA	33	-	-	
	KRA119S		V _O =-5V, I _O =-10mA	30	-	-	
	KRA120S		V _O =-5V, I _O =-10mA	24	-	-	
	KRA121S		V _O =-5V, I _O =-5mA	33	-	-	
	KRA122S		V _O =-5V, I _O =-5mA	62	-	-	
Output Voltage	KRA116S	V _{O(ON)}	I _O =-10mA, I _I =-0.5mA	-	-	-0.3	V
	KRA117S		I _O =-10mA, I _I =-0.5mA	-	-0.1	-0.3	
	KRA118S		I _O =-10mA, I _I =-0.5mA	-	-	-0.3	
	KRA119S		I _O =-10mA, I _I =-0.5mA	-	-0.1	-0.3	
	KRA120S		I _O =-10mA, I _I =-0.5mA	-	-0.1	-0.3	
	KRA121S		I _O =-10mA, I _I =-0.5mA	-	-0.1	-0.3	
	KRA122S		I _O =-5mA, I _I =-0.25mA	-	-0.1	-0.3	
Input Voltage (ON)	KRA116S	V _{I(ON)}	V _O =-0.3V, I _O =-20mA	-	-0.98	-3	V
	KRA117S		V _O =-0.3V, I _O =-20mA	-	-1.83	-3	
	KRA118S		V _O =-0.3V, I _O =-20mA	-	-1.22	-3	
	KRA119S		V _O =-0.3V, I _O =-20mA	-	-1.76	-2.5	
	KRA120S		V _O =-0.3V, I _O =-2mA	-	-2	-3	
	KRA121S		V _O =-0.3V, I _O =-2mA	-	-3.9	-5	
	KRA122S		V _O =-0.3V, I _O =-1mA	-	-1.64	-3	
Input Voltage (OFF)	KRA116S	V _{I(OFF)}	V _{CC} =-5V, I _O =-100μA	-0.3	-0.63	-	V
	KRA117S			-0.5	-1.15	-	
	KRA118S			-0.3	-0.67	-	
	KRA119S			-0.3	-0.82	-	
	KRA120S			-0.8	-1.68	-	
	KRA121S			-1	-3.09	-	
	KRA122S			-0.5	-1.17	-	
Transition Frequency	KRA116S ~ 122S	f _{T*}	V _O =-10V, I _O =-5mA	-	250	-	MHz
Input Current	KRA116S	I _I	V _I =-5V	-	-	-7.2	mA
	KRA117S			-	-	-3.8	
	KRA118S			-	-	-3.8	
	KRA119S			-	-	-1.8	
	KRA120S			-	-	-0.88	
	KRA121S			-	-	-0.16	
	KRA122S			-	-	-0.15	

Note : *Characteristic of Transistor Only