

KE724503

Darlington Three-Phase Bridge - Visolation 2.5kV(RMS)

Powerex Power Semiconductors

Isolated Case (Y/N)=Yes

Circuits Per Package=1

V(BR)CEO (V)=450

V(BR)CBO (V)=600

I(C) Abs. (A) Collector Current=30

Absolute Max. Power Diss. (W)=210

R(thJC) (j ¢C/W)=600m

h(FE) Min. Static Current Gain=75

@I(C) (A) (Test Condition)=30

@VCE (test)=2.0

V(CE)sat Max. (V)=2.0

@I(C) (A) (Test Condition)=30

@I(B) (A) (Test Condition)=400m

t(r) Max. (s) Rise time=1.5u

t(f) Max. (s) Fall time.=3.0u

Package=Module-q