

RT3AMMM

Composite Transistor
For Low Frequency Amplify Application
Silicon Pnp Epitaxial Type

DESCRIPTION

RT3AMMM is a composite transistor built with two 2SA1235A chips in SC-88 package.

FEATURE


- Silicon pnp epitaxial type
- Each transistor elements are independent.
- Mini package for easy mounting

APPLICATION

For low frequency amplify application

OUTLINE DRAWING


Unit:mm



MAXIMUM RATING (Ta=25°C)

SYMBOL	PARAMETER	RATING	UNIT
VCBO	Collector to Base voltage	-60	V
VEBO	Emitter to Base voltage	-6	V
VCEO	Collector to Emitter voltage	-50	V
IC	Collector current	-200	mA
PC	Collector dissipation (Total, Ta=25°C)	150	mW
Tj	Junction temperature	+125	°C
Tstg	Storage temperature	-55 ~ +125	°C

MARKING



RT3AMMM

Composite Transistor
For Low Frequency Amplify Application
Silicon Pnp Epitaxial Type

ELECTRICAL CHARACTERISTICS (Ta=25°C)






Symbol	Parameter	Test conditions	Limits			Unit
			Min	Typ	Max	
V(BR)CEO	Collector to Emitter break down voltage	IC=100 μ A, RBE= ∞	-50	-	-	V
ICBO	Collector cut off current	VCB=-60V, IE=0	-	-	-0.1	μ A
IEBO	Emitter cut off current	VEB=-6V, IC=0	-	-	-0.1	μ A
hFE*	DC forward current gain	VCE=-6V, IC=-1mA	150	-	500	-
hFE	DC forward current gain	VCE=-6V, IC=-0.1mA	90	-	-	-
VCE(sat)	Collector to Emitter saturation voltage	IC=-100mA, IB=-10mA	-	-	-0.3	V
fT	Gain band width product	VCE=-6V, IE=10mA	-	200	-	MHZ
Cob	Collector output capacitance	VCB=-6V, IE=0, f=1MHZ	-	4.0	-	pF
NF	Noise figure	VCE=6V, IE=0.3mA, f=100Hz, RG=10k Ω	-	-	20	dB

* : It shows hFE classification in right table.

item	E	F
hFE	150~300	250~500

RT3AMMM

Composite Transistor
For Low Frequency Amplify Application
Silicon Pnp Epitaxial Type





Marketing division, Marketing planning department

6-41 Tsukuba, Isahaya, Nagasaki, 854-0065 Japan

Keep safety first in your circuit designs!

• ISAHAYA Electronics Corporation puts the maximum effort into making semiconductor products better and more reliable, but there is always the possibility that trouble may occur with them. Trouble with semiconductors may lead to personal injury, fire or property damage. Remember to give due consideration to safety when making your circuit designs, with appropriate measures such as (1) placement of substitutive, auxiliary, (2) use of non-flammable material or (3) prevention against any malfunction or mishap.

Notes regarding these materials

- These materials are intended as a reference to our customers in the selection of the ISAHAYA products best suited to the customer's application; they don't convey any license under any intellectual property rights, or any other rights, belonging ISAHAYA or third party.
- ISAHAYA Electronics Corporation assumes no responsibility for any damage, or infringement of any third party's rights, originating in the use of any product data, diagrams, charts or circuit application examples contained in these materials.
- All information contained in these materials, including product data, diagrams and charts, represent information on products at the time of publication of these materials, and are subject to change by ISAHAYA Electronics Corporation without notice due to product improvements or other reasons. It is therefore recommended that customers contact ISAHAYA Electronics Corporation or an authorized ISAHAYA products distributor for the latest product information before purchasing product listed herein.
- ISAHAYA Electronics Corporation products are not designed or manufactured for use in a device or system that is used under circumstances in which human life is potentially at stake. Please contact ISAHAYA electronics corporation or an authorized ISAHAYA products distributor when considering the use of a product contained herein for any specific purposes, such as apparatus or systems for transportation, vehicular, medical, aerospace, nuclear, or undersea repeater use.
- The prior written approval of ISAHAYA Electronics Corporation is necessary to reprint or reproduce in whole or in part these materials.
- If these products or technologies are subject to the Japanese export control restrictions, they must be exported under a license from the Japanese government and cannot be imported into a country other than the approved destination. Any diversion or re-export contrary to the export control laws and regulations of Japan and/or the country of destination is prohibited.
- Please contact ISAHAYA Electronics Corporation or authorized ISAHAYA products distributor for further details on these materials or the products contained therein.