THIS DRAWING IS UNPUBLISHED. RELEASED FOR PUBLICATION -.-.-
© COPYRIGHT -- BY TYCO ELECTRONICS CORPORATION. ALL RIGHTS RESERVED.

LOC	DIST
GP	00

REVISIONS

P	LTR	DESCRIPTION	DATE	DWN	APVD
	B	REVISED PER ECO-10-019804	28OCT10	HMR	JL

1. RECOMMENDATIONS FOR 2.36 [.093] TO 3.18 [.125] THICK PC BOARD:
   A. HOLE DIAMETER AFTER DRILLING = 1.151±0.025 [.0453±.0010].
   B. HOLE DIAMETER AFTER TIN PLATING = 0.94 [.037]–1.09 [.043].
   C. HOLE DIAMETER AFTER REFLOW = 0.91 [.036]–1.09 [.043].
   D. PC BOARD PLATING TO BE 0.76µm [.000300] MIN TIN OVER 0.05±0.03 [.002±.001] COPPER.
2. HOUSING: FLAME RETARDANT, UL 94V–0 RATED, GLASS FILLED, NYLON OR POLYESTER, BLACK.
3. CONTACTS: COPPER ALLOY
4. SHELL: CARBON STEEL
5. SCREWLOCKS: ZINC ALLOY
6. SHELL: 5.08µm [.000200] MIN TIN OVER 2.54µm [.000100] MIN COPPER.
7. CONTACTS:
   0.76 MICRO METERS [.000030] MINIMUM GOLD IN MATING AREA.
   2.54 MICRO METERS [.000100] MINIMUM TIN ON COMPLIANT PIN.
   ALL OVER 1.27 MICRO METERS [.000050] MINIMUM NICKEL.
   OR
   GOLD FLASH OVER PALLADIUM NICKEL.
   0.76 MICRO METERS [.000030] MINIMUM TOTAL IN MATING AREA.
   2.54 MICRO METERS [.000100] MINIMUM TIN ON COMPLIANT PIN.
   ALL OVER 1.27 MICRO METERS [.000050] MINIMUM NICKEL.
8. SCREWLOCKS: CLEAR CHROMATE









RECOMMENDED PC BOARD MOUNTING DIMENSIONS 1

COPYRIGHT 2005
TYCO ELECTRONICS CORP
ALL RIGHTS RESERVED

5750060–1
PART NO

THIS DRAWING IS A CONTROLLED DOCUMENT.

DIMENSIONS: INCHES
TOLERANCES UNLESS OTHERWISE SPECIFIED:
2 PLC ± –
3 PLC ± –
4 PLC ± 0.13 [.005]
5 PLC ± –
ANGLES ± 2°
MATERIAL 2 3 4 5
FINISH 6 7 8

DWN	J. ALCORTA – 30CT05
CHK	S. BOLASH – 01-26-06
APVD	M. WALMSLEY – 01-26-06
PRODUCT SPEC	108–40014
APPLICATION SPEC	114–40026
WEIGHT	–
CUSTOMER DRAWING	

Tyco Electronics Corporation
Harrisburg, PA 17105–3608

NAME: PLUG ASSEMBLY, SIZE 4, 37 POSITION, MEDIUM PROFILE, ACTION PIN, FRONT METAL SHELL, AMPLITE HD–20

SIZE	CAGE CODE	DRAWING NO	RESTRICTED TO
A1	00779	C–5750060	–

SCALE 4:1 SHEET 1 OF 1 REV B

AMP 4805 REV 31MAR2000

11NOV05 12:16pm us018845 P:\Gerace\0037\5750060_1–c.dwg

Downloaded from Elcodis.com electronic components distributor