

Anti-surge thick film chip resistor

ESR03 (0603 size : 1 / 5W)

Features

- 1) Power rating of 1 / 5W (MCR03 1/10W)
- 2) Superior anti surge to MCR series
- 3) Highly reliable chip resistor
- Ruthenium oxide dielectric offers superior resistance to the elements.
- 4) ROHM resistors have approved ISO-9001, ISO/TS 16949 certification.

Design and specifications are subject to change without notice. Carefully check the specification sheet before using or ordering it.

Applications

Automotive, LCD Monitor, projector, power supply, charger, inverter and so on.

Ratings

| Item | Conditions | Specifications |
|-----------------------|---|------------------------------|
| Rated power | Power must be derated according to the power derating curve in Figure 1 when ambient temperature exceeds 70°C. | 0.2W (1/5W) at 70°C |
| Rated voltage | The voltage rating is calculated by the following equation. If the value obtained exceeds the limiting element voltage, the voltage rating is equal to the maximum operating voltage. E: Rated voltage (V) $E=\sqrt{P \times R}$ P: Rated power (W) R: Nominal resistance (Ω) | Limiting element voltage 50V |
| Nominal resistance | See Table 1. | |
| Operating temperature | | –55°C to +155°C |

Table 1

| Resistance tolerance | Resistance (Ω) | 0 | Resistance temperature coefficient (ppm/°C) |
|----------------------|-------------------|-------|--|
| D (±0.5%) | $10 \le R \le 1M$ | (E24) | ±100 |
| F (±1%) | $1 \le R \le 10M$ | (E24) | ±100 |
| J (±5%) | $1 \le R \le 10M$ | (E24) | ±200 |


•Before using components in circuits where they will be exposed to transients such as pulse loads (short-duration, high- level loads), be certain to evaluate the component in the mounted state. In addition, the reliability and performance of this component cannot be guaranteed if it is used with a steady state voltage that is greater than its rated voltage.

ESR03


Characteristics

| Item | Guaranteed value Resistor type | - Test conditions (JIS C 5201-1) |
|--|--|--|
| Resistance | J : ±5% F : ±1% D : ±0.5% | JIS C 5201-1 4.5 |
| Variation of resistance with temperature | See Table.1 | JIS C 5201-1 4.8 Measurement : -55 / +25 / +125°C |
| Overload | ± (2.0%+0.1Ω) | JIS C 5201-1 4.13 Rated voltage (current) ×2.5, 2s. Maximum overload voltage : 100V |
| Solderability | A new uniform coating of minimum of 95% of the surface being immersed and no soldering damage. | JIS C 5201-1 4.17 Rosin-Ethanol (25%WT) Soldering condition : 235±5°C Duration of immersion : 2.0±0.5s. |
| Resistance to soldering heat | \pm (1.0%+0.05 $\Omega)$ No remarkable abnormality on the appearance. | JIS C 5201-1 4.18 Soldering condition : 260±5°C Duration of immersion : 10±1s. |
| Rapid change of temperature | ± (1.0%+0.05Ω) | JIS C 5201-1 4.19 Test temp. : -55°C to +125°C 5cyc |
| Damp heat, steady state | ± (3.0%+0.1Ω) | JIS C 5201-1 4.24 40°C, 93%RH Test time : 1,000h to 1,048h |
| Endurance at 70°C | ± (3.0%+0.1Ω) | JIS C 5201-1 4.25.1 Rated voltage (current), 70°C 1.5h : ON – 0.5h : OFF Test time : 1,000h to 1,048h |
| Endurance | ± (3.0%+0.1Ω) | JIS C 5201-1 4.25.3 155°C Test time : 1,000h to 1,048h |
| Resistance to solvent | ± (1.0%+0.05Ω) | JIS C 5201-1 4.29 23±5°C, Immersion cleaning, 5±0.5min Solvent : 2-propanol |
| Bend strength of the end face plating | \pm (1.0%+0.05 $\Omega)$ Without mechanical damage such as breaks. | JIS C 5201-1 4.33 |
| Static electric characteristics | ± (5.0%+0.05Ω) | $\begin{array}{l} \mbox{EIAJ ED-4701 1300 Test method 304} \\ \mbox{Voltage : } 3kv \\ \mbox{R : } 1.5k\Omega \\ \mbox{C : } 100pF \\ \mbox{Apply cycle : 1 time} \end{array}$ |


•Dimensions (Unit : mm)



Packaging



•Part No. Explanation



Packaging Specifications Code

| I | Part No. | Code | Resistance tolerance | | | Deskezing enerifications | Reel | |
|---|----------|------|----------------------|--------|----------|--------------------------|----------------|--------------------------|
| l | Part No. | Code | J(±5%) | F(±1%) | D(±0.5%) | Packaging specifications | Reel | Basic ordering unit(pcs) |
| | ESR03 | EZP | 0 | O | 0 | Paper tape (4mm Pitch) | φ180mm (7inch) | 5,000 |

Reel (\u00c0180mm) : Compatible with JEITA standard "EIAJ ET-7200B"

| | Notes |
|--|---|
| | ng or reproduction of this document, in part or in whole, is permitted without the f ROHM Co.,Ltd. |
| The conte | nt specified herein is subject to change for improvement without notice. |
| "Products | nt specified herein is for the purpose of introducing ROHM's products (hereinafte "). If you wish to use any such Product, please be sure to refer to the specifications be obtained from ROHM upon request. |
| illustrate t | of application circuits, circuit constants and any other information contained herein he standard usage and operations of the Products. The peripheral conditions mus nto account when designing circuits for mass production. |
| However, | e was taken in ensuring the accuracy of the information specified in this document should you incur any damage arising from any inaccuracy or misprint of sucl n, ROHM shall bear no responsibility for such damage. |
| examples implicitly, other part | ical information specified herein is intended only to show the typical functions of and of application circuits for the Products. ROHM does not grant you, explicitly o any license to use or exercise intellectual property or other rights held by ROHM and ies. ROHM shall bear no responsibility whatsoever for any dispute arising from the h technical information. |
| equipmen | icts specified in this document are intended to be used with general-use electronic t or devices (such as audio visual equipment, office-automation equipment, commu evices, electronic appliances and amusement devices). |
| The Produ | cts specified in this document are not designed to be radiation tolerant. |
| | HM always makes efforts to enhance the quality and reliability of its Products, a ay fail or malfunction for a variety of reasons. |
| against th failure of a shall bear | sure to implement in your equipment using the Products safety measures to guard e possibility of physical injury, fire or any other damage caused in the event of the any Product, such as derating, redundancy, fire control and fail-safe designs. ROHM no responsibility whatsoever for your use of any Product outside of the prescribed not in accordance with the instruction manual. |
| system wi may result instrument fuel-contro any of the | acts are not designed or manufactured to be used with any equipment, device on hich requires an extremely high level of reliability the failure or malfunction of which t in a direct threat to human life or create a risk of human injury (such as a medica t, transportation equipment, aerospace machinery, nuclear-reactor controller oller or other safety device). ROHM shall bear no responsibility in any way for use o Products for the above special purposes. If a Product is intended to be used for an ial purpose, please contact a ROHM sales representative before purchasing. |
| be control | nd to export or ship overseas any Product or technology specified herein that may led under the Foreign Exchange and the Foreign Trade Law, you will be required to cense or permit under the Law. |



Thank you for your accessing to ROHM product informations. More detail product informations and catalogs are available, please contact us.

ROHM Customer Support System

http://www.rohm.com/contact/