



CBC-2 TFT Displays Supports List

Rev XB 9/20/2010

Panel Size	Manufacturer	Part Number	Display Resolution	Touch Panel	Touch Panel Connector	Display Connector	SW3 J3-P30	SW7 J3-P31	SW8 J3-P32	SW11	Backlight Type	Backlight I / V (LED)	R23 Res Value	R20 -R22 Value	Backlight Resistor Values
5.7	Densitron	84-0084-000	320 x 240	No		J3	R / L	U / D	Open		LED	200mA / 10V	100K	1 Ohms	No Change
5.7	Hantronix	HDA570ST-V	320 x 240	YES	J14	J3	R / L Low	U / D Hi	Open		LED	75mA / 27.5V	330K	2.67	Change to resistor value from the table
5.7	Hantronix	HDA570ST-VH	320 x 240	YES	J14	J3	R / L Low	U / D Hi	Open		LED	200mA / 10V	100K	1 Ohms	No Change
5.7	Hantronix	HDA570S-VH	320 x 240	No		J3	R / L Low	U / D Hi	Open		LED	200mA / 10V	100K	1 Ohms	No Change
5.7	Kyocera	TCG057QVLAC-G00	320 x 240	No		J3	R / L	U / D	GND		LED	75mA / 23.1V	330K	2.67	Change to resistor value from the table
5.7	Kyocera	TCG057QVLAD-G00	320 x 240	YES	J13	J3	R / L	U / D	GND		LED	75mA / 23.1V	330K	2.67	Change to resistor value from the table
5.7	Kyocera	TCG057QVLAP-G00	320 x 240	No		J3	R / L	U / D	GND		LED	75mA / 23.1V	330K	2.67	Change to resistor value from the table
5.7	Kyocera	TCG057QVLAQ-G00	320 x 240	YES	J13	J3	R / L	U / D	GND		LED	75mA / 23.1V	330K	2.67	Change to resistor value from the table
5.7	Kyocera	TCG057QVLAR-G00	320 x 240	YES	J13	J3	R / L	U / D	GND		LED	75mA / 23.1V	330K	2.67	Change to resistor value from the table
5.7	Kyocera	TCG057VGLAC-G000	640 x 480	No		J3	R / L	U / D	3.3V		LED	75mA / 23.1V	330K	2.67	Change to resistor value from the table
5.7	Kyocera	TCG057VGLAD-G000	640 x 480	YES	J13	J3	R / L	U / D	3.3V		LED	75mA / 23.1V	330K	2.67	Change to resistor value from the table
5.7	Kyocera	TCG057VGLAG-G000	640 x 480	YES	J13	J3	R / L	U / D	3.3V		LED	75mA / 23.1V	330K	2.67	Change to resistor value from the table
5.7	Kyocera	THG057VGLAC-H000	640 x 480	No		J3	R / L	U / D	Open		LED	75mA / 23.1V	330K	2.67	Change to resistor value from the table
5.7	Kyocera	THG057VGLAJ-H000	640 x 480	YES	J13	J3	R / L	U / D	Open		LED	75mA / 23.1V	330K	2.67	Change to resistor value from the table
5.7	Microtips	MTF-TV57NN721-AV	640 x 480	No		J3	R / L	U / D	Open		LED	200mA / 10V	100K	1 Ohms	No Change
5.7	Microtips	MTF-TV57NP721-AV	640 x 480	YES	J14	J3	R / L	U / D	Open		LED	200mA / 10V	100K	1 Ohms	No Change
5.7	Okaya	RH320240T-5X7WP-A9Y1	320 x 240	YES	J14	J3	R / L	U / D	Open		LED	75mA / 23.5V	330K	2.67	Change to resistor value from the table
5.7	Optrex	T-55265GD057-J-LW-ABN	320 x 240	No		J3	R / L	U / D	Open		LED	180mA / 13.2V	100K	1 Ohms	No Change
5.7	Optrex	T-55265GD057-J-LW-ACN	320 x 240	YES	J13	J3	R / L	U / D	Open		LED	180mA / 13.2V	100K	1 Ohms	No Change
5.7	OSD	OSD057T0674-29TS	320 x 240	YES	J14	J3	Low	High	Open		LED	200mA / 9.6V	100K	1 Ohms	No Change
5.7	OSD	OSD057T0673-29TS	320 x 240	YES	J14	J3	Low	High	Open		LED	60mA / 23.1V	330K	2.67	Change to resistor value from the table
5.7	PrimView	PD057VU7	320 x 240	YES	J13	J3	R / L	U / D	Low		LED	75mA / 23.5V	330K	2.67	Change to resistor value from the table
5.7	PrimView	PD057VT4	640 x 480	YES	J13	J3	Low	High	3.3V		LED	240mA / 11V	100K	0.83Ohms	No Change
5.7	Shelly	SCA057P3224T-A201	320 x 240	No	J14	J3	R / L	U / D	Open		LED	200mA / 10V	100K	1 Ohms	No Change
5.7	Tianma	TM057QDH01	640 x 480	No		J3	R / L	U / D	Open		LED	75mA / 23.5V	330K	2.67	Change to resistor value from the table
5.7	Tianma	TM057KDH01	320 x 240	No		J3	R / L	U / D	Open		LED	75mA / 23.5V	330K	2.67	Change to resistor value from the table