

Piezoelectric Buzzer (Built-In Drive)

Date: 6/8/06

Dimensions: mm (In.)


Part Number:

254-15210-ROX

Piezoelectric Buzzer (Built-In Drive)

REMOVE AFTER WASHING





KT-400269

Electrical Specifications:

- Resonant frequency: 4± .5KHz
- Allowable input voltage: 3~15VDC
- Current consumption: 6mA max. @ 6VDC
- · Sound Pressure: 90dB min./ 9VDC/ 10cm

Note:

· RoHS Compliant by Exemption

Mechanical Specifications:

• Operating temperature: -20°C~+105°C

Materials:

- · Case: PC UL94V2
- Pin pitch: .299"± .012"; tin plated brass

Available from Mouser Electronics

www.mouser.com

(800) 346-6873