


# SANYO DENKI 103H546 - 0440 Stepper Motor

MODEL □	Step Angle Deg/Step	Voltage V	Current A/Phase	Resistance Ω /Phase	Inductance mH/Phase	Holding Torque kg · cm	Rotor Inertia g · cm <sup>2</sup>	Weight kg
103H546-0440	1.8	3.15	1	3.15	2.8	1.5	30	0.2

★ Replace this with a common connector.



Housing : EHR-6(JST)  
Connector: SEH-001T-P0.6(JST)

