

80W Switching Mode DC Power Supply

3-in-1 Power Supply

Three output ranges perform like 3 power supplies in one

Features:

- Constant voltage or current
- 3 selectable ranges:
 - 0.10 to 16.40V/0.100 to 5.100A
 - 0.10 to 27.60V/0.100 to 3.100A
 - 0.10 to 36.80V/0.100 to 2.300A
- 4-Digit LED displays
- Front/Rear output terminals
- Remote sensing for accurate applied voltage at load point
- Compact slim tower housing is ideal for tight work bench
- Lightweight for easy portability
- Complete with AC Power cord



Current limited DC supply for electronic repair and calibration

| Specifications | | | |
|---------------------------|----------------------------------|-----------------|-----------------|
| Voltage Output (3 ranges) | 0.10 to 16.40V | 0.10 to 27.60V | 0.10 to 36.80V |
| Current Output (3 ranges) | 0.100 to 5.100A | 0.100 to 3.100A | 0.100 to 2.300A |
| Basic accuracy | ±1% | | |
| Ripple & Noise | <30mVpp | | |
| Line Regulation | <4mV | | |
| Load Regulation | <20mV | | |
| Display | Dual 4-digit LED displays | | |
| Power | 90-264VAC; 47-63Hz | | |
| Dimensions | 13 x 5 x 2" (330 x 127 x 53.5mm) | | |
| Weight | 4.2lbs (1.9kg) | | |

Ordering Information:

38226080W Switching Mode DC Power Supply

