



REVISIONS

DOC. NO. SPC-F004 * Effective: 7/8/02 * DCP No: 1398

DCP #	REV	DESCRIPTION	DRAWN	DATE	CHECKD	DATE	APPRVD	DATE
1754	A	RELEASED	DCM	11/19/05	HO	11/21/05	JWM	11/21/05



- Two Digital Panel Meters
- 0.01 % High Regulation
- Constant Voltage and Constant Current Operation
- High Efficiency
- High Power Density
- Over Voltage Protection
- Remote Control Output ON/OFF Function

SPECIFICATIONS

OUTPUT	Voltage	60V
	Current	6A
Constant Voltage Operation	Regulation	Line regulation $\leq 5mV$ Load regulation $\leq 5mV$
	Ripple & Noise	$\leq 5mV_{rms}$, 100mVp-p 20Hz ~ 20MHz
	Recovery Time	$\leq 500 \mu S$ (50% Load change, Minimum load 0.5A)
	Temp. Coefficient	$\leq 100ppm / ^\circ C$
	Output Range	0 to rated voltage, continuously adjustable
Constant Current Operation	Regulation	Line regulation $\leq 3mA$ Load regulation $\leq 3mA$
	Ripple Current	$\leq 3mA_{rms}$
	Output Range	0 to rated current continuously adjustable (HI/LO range switchable)
METER	Digital	3 1/2 digits, 0.39" LED display Accuracy $\pm (0.5\% \text{ of rdg} + 2\text{digits})$
	Chassis and Terminal	$20M\Omega$ or above (DC 500V)
INSULATION	Chassis and AC Cord	$30M\Omega$ or above (DC 500V)
	POWER SOURCE	AC 115V/ 230V $\pm 15 \%$, 50/60Hz
ACCESSORIES	Instruction manual, Power cord, Test lead	
DIMENSIONS & WEIGHT	128(W) x 145(H) x 285(D) mm, Approx. 3.2 kg.	

SPC-F004.DWG

TOLERANCES: UNLESS OTHERWISE SPECIFIED, DIMENSIONS ARE FOR REFERENCE PURPOSES ONLY.	DRAWN BY:	DATE:	DRAWING TITLE:			
	Daniel McVicker	11/19/05	Switching DC Power Supply			
	CHECKED BY:	DATE:	SIZE	DWG. NO.	ELECTRONIC FILE	REV
	HO	11/21/05	A	72-7705	96H1240.dwg	A
APPROVED BY:	DATE:	SCALE:	U.O.M.: INCHES [mm]	SHEET: 1 OF 1		
JWM	11/21/05	NTS				

ALL RIGHTS RESERVED. NO PORTION OF THIS PUBLICATION, WHETHER IN WHOLE OR IN PART CAN BE REPRODUCED WITHOUT THE EXPRESS WRITTEN CONSENT OF SPC TECHNOLOGY. DISCLAIMER: ALL STATEMENTS AND TECHNICAL INFORMATION CONTAINED HEREIN ARE BASED UPON INFORMATION AND/OR TESTS WE BELIEVE TO BE ACCURATE AND RELIABLE. SINCE CONDITIONS OF USE ARE BEYOND OUR CONTROL, THE USER SHALL DETERMINE THE SUITABILITY OF THE PRODUCT FOR THE INTENDED USE AND ASSUME ALL RISK AND LIABILITY WHATSOEVER IN CONNECTION THEREWITH.