



SDS-100B Series - 100W Single Output Enclosed DC-DC Converter

Home > Products > Enclosed > 100W Single Output Enclosed DC-DC Converter

Features	Standards
<ul style="list-style-type: none">24V DC InputInrush current limitation soft start functionInput & output isolationInput polarity reverse protectionInput under / over voltage protectionOver load, over voltage & short circuit protectionFR4 glas epoxy double side circuit board, meets UL-94V0 which could work in an environment with high vibrationCurrent sharing (optional)Output voltage $\pm 10\%$ adjustment100% 50°C burn-in testMeets UL, cUL, TUV, CB, CE standard	 

Specification	
Input Voltage	19VDC ~ 36VDC. Typical 24V.
Input Current	<8A@19V DC
Inrush Current	<30A@24V DC
Under Input Voltage	<15VDC ~ 18VDC
Over Input Voltag	>37VDC ~ 42VDC
Over Load Protection	Over 105% ~ 180% of rating, recovers automatically after fault condition has been removed.
Short Circuit Protection	Shutdown, recovers automatically after fault condition has been removed.
Rise Time	<50mS
Current Sharings	Optional
Cooling	Natural Cooling
Operating Temperature	0°C ~ 70°C; derating: 50°C ~70°C : 2.5%/°C.
Operating Humidity	20% ~ 85% non condensing
Storage Temperature	-10°C ~ +75°C
Storage Humidity	Storage: 10% ~ 95% non condensing
M.T.B.F.	262K hours
Safety	Meet UL 60950, CSA C22.2 No.60950, TUV EN 60950, IEC 60950, EMKO-TSE (74-SEC)207/94
EMI	EN 55022 CLASS B FCC CFR 47 PART 15 CLASS B CNS 13438 CLASS B
EMS	EN 55024 : EN 61000-4-2-,3,4,5,5,6,8.

Items

SDS- 100B Series

Part No	Voltage	Min Load	Max Load	Regulation	Ripple Noise (MAX)	Efficiency (TYP)	Max Power	Over Voltage Protection
<u>SDS-100B3.3</u>	3.3V	0A	25A	±3%	40mV	68%	83W	3.8V ~ 4.6V
<u>SDS-100B05</u>	5V	0A	20A	±2%	50mV	72%	100W	5.8V ~ 7.0V
<u>SDS-100B12</u>	12V	0A	8.5A	±1%	100mV	75%	100W	13.8V ~ 17.5V
<u>SDS-100B24</u>	24V	0A	4.2A	±1%	150mV	78%	100W	27.6V ~ 33.6V
<u>SDS-100B48</u>	48V	0A	2.1A	±1%	250mV	84%	100W	55.2V ~ 67.2V

© Copyright 2006 Sunpower UK : [Website design, hosting & Technology: Strategies Group Plc](#)