# 15 SERIES MOULDED CASE CURRENT TRANSFORMERS



#### **DESCRIPTION**

Two small moulded case current transformers suitable for primary currents from 1A to 500A using cable or bar primaries

#### **APPLICATION**

For use where space is limited within the panel, and where a built in choice of fixing methods is required.









Busbar mounting



- Three built in fixing methodsBase, Din Rail & Busbar mounting
- Built in hinged terminal cover
- Terminals suitable for screw or push on connectors
- Small size enables mounting where busbars run close together
- Case moulded in high impact polyester
- Secondary terminals with double layout
- Primary ranges from 1A to 500A



DIN rail mounting

Base mounting



Hinged terminal cover

#### **TECHNICAL OVERVIEW**

- Conforms to IEC 44-1 / IEC 185, BS 7626
- Insulation level 0.72/3kV
- Ambient temperature range -20° to 70°c
- Self extinguishing to UL94VO
- Enclosure to IP20
- CE approved
- Manufactured to ISO 9002

# 15 SERIES MOULDED CASE CURRENT TRANSFORMERS



## **TYPE 151**

Type: 151-5 5A Secondary 151-1 1A Secondary

_	131 1 17 (Secondary													
	CLASS 3						CI	_ASS	1	CLASS 0.5				
VA Primary	2.5	5	7.5	10	15	2.5	5	7.5	10	15	2.5	5	7.5	10
1 /	Α1	A2	-	A4	-	A6	Α7	-	-	-	-	-	-	-
2.5			-		-	В6		-	-	-	-	-	-	-
5	C1	C2	-	C4	-	C6	C7	-	-	-	-	-	-	-
7.5	D1	D2	-	D4	-	D6	D7	-	-	-	-	-	-	-
8	E1	E2	-	E4	-	E6	E7	-	-	-	-	-	-	-
10	F1	F2	-	F4	-	F6	F7	-	-	-	-	-	-	-
15	G1	G2	-	G4	-	G6	G7	-	-	-	-	-	-	-
20	H1	H2	-	H4	-	Н6	H7	-	-	-	-	-	-	-
25	J1	J2	-	J4	-	J6	J7	-	-	-	-	-	-	-
30	K1	K2	-	K4	-	K6	K7	-	-	-	-	-	-	-
40	L1	L2	-	L4	-	L6	L7	-	-	-	-	-	-	-
50 N	M1	M2	-	-	-	M6	-	-	-	-	-	-	-	-
60 I	N1	N2	-	N4	-	N6	-	-	-	-	-	-	-	-
75	P1	P2	-	P4	-	P6	-	-	-	-	-	-	-	-
80	R1	R2	-	R4	-	R6	-	-	-	-	-	-	-	-
100	S1	S2	-	S4	-	S6	S7	-	-	-	S11	-	-	-


Denotes double wound / wound primary

#### **SUITABLE FOR:**

Cables up to 14mm outside diameter, or a conducting bush 14mm wide.

#### **ORDER EXAMPLE:**

A 50/5A 2.5VA class 1 current transformer is product code 151-5-M6.



## **TYPE 153**

Type: 153-5 5A Secondary 153-1 1A Secondary


		CLA	ASS 3	3		CLASS 1					CLASS 0.5				
<b>VA</b> Primary	2.5	5	7.5	10	15	2.5	5	7.5	10	15	2.5	5	7.5	10	
75	P1	-	-	-	-	-	-	-	-	-	-	-	-	-	
80	R1	-	-	-	-	-	-	-	-	-	-	-	-	-	
100	<b>S</b> 1	-	-	-	-	S6	-	-	-	-	-	-	-	-	
150	T1	T2	-	-	-	T6	T7	-	-	-	T11	-	-	-	
200	V1	V2	-	-	-	V6	V7	-	-	-	V11	V12	-	-	
250	W1	W2	-	-	-	W6	W7	-	-	-	W11	W12	-	-	
300	X1	X2	X3	-	-	X6	X7	-	-	-	X11	X12	-	-	
400	Y1	Y2	-	Y4	-	Y6	Y7	Y8	-	-	Y11	Y12	Y13	Y14	
500	Z1	Z2	-	Z4	-	Z6	Z7	-	Z9	-	Z11	Z12	Z13	Z14	

#### **SUITABLE FOR:**

Cables up to 26mm outside diameter, bars up to 30mm wide or a conducting bush 24mm wide.

#### **ORDER EXAMPLE:**

A 200/1A 5VA class 3 current transformer is product code 153-1-V2.



### STANDARD ACCESSORIES

- Type 151 and 153 are supplied with 4off M4 x 10 pan head with lock washers plus 2off 6.3 x 0.8 push on blades.
- Type 153 is supplied with 2off M4 x 40 pan head pozidrive screws
- Other fixing accessories available on request.

Our policy is one of continuous development and therefore specifications may change without notice.

# **HOWARD BUTLER LTD**

CROWN WORKS, LINCOLN ROAD WALSALL WS1 2EB ENGLAND