

# 9V Ni-Cad / Ni-MH Plug-in Battery Charger



## Features:

- Charges 1 to 2 9V Ni-Cad / Ni-MH batteries in 3 to 4 hours.
- 2 individual charging channels.
- Automatically switches to trickle charge after full charge.
- $-\Delta V$  charging.
- Discharge function.
- Automatically switches to trickle charge after full charge.
- LED charge status indicators.
- UK plug.

## Electrical Data:

<b>Input</b>	Input Voltage / Frequency	230V / 50HZ
	Input Power	4.7W
<b>Output</b>	Rated Output Voltage	9.8V
	Rate Fast Charging Current	70mA
	Rated Output Power	1.4VA
<b>Resistance</b>	Insulation Resistance	100M $\Omega$ (measured with 500 V DC)
<b>Protection</b>	Thermal Protection	Thermal fuse:125°C / 2A
	Withstand Voltage (Hi-Pot)	3750V AC 50Hz for 1minute or 4000V AC 2seconds

## Mechanical Data:

<b>Supply Connection Type</b>	UK
<b>Primary Turns and Wire Gauge</b>	4950 / 0.07mm
<b>Secondary Turns and Wire Gauge</b>	400T / 0.27mm
<b>Core Size</b>	35 x 13mm
<b>Output Plug Dimensions</b>	-----
<b>Polarity</b>	-----
<b>Unit Weight</b>	223g

## Part Number Table

Description	Part Number
Charger, 9V Plug-In NICD/NIMH	MW6288UK

**Disclaimer** This data sheet and its contents (the "Information") belong to the Premier Farnell Group (the "Group") or are licensed to it. No licence is granted for the use of it other than for information purposes in connection with the products to which it relates. No licence of any intellectual property rights is granted. The Information is subject to change without notice and replaces all data sheets previously supplied. The Information supplied is believed to be accurate but the Group assumes no responsibility for its accuracy or completeness, any error in or omission from it or for any use made of it. Users of this data sheet should check for themselves the Information and the suitability of the products for their purpose and not make any assumptions based on information included or omitted. Liability for loss or damage resulting from any reliance on the Information or use of it (including liability resulting from negligence or where the Group was aware of the possibility of such loss or damage arising) is excluded. This will not operate to limit or restrict the Group's liability for death or personal injury resulting from its negligence. SPC Multicomp is the registered trademark of the Group. © Premier Farnell plc 2010.

<http://www.farnell.com>  
<http://www.newark.com>  
<http://www.cpc.co.uk>

