Part Numbering

PTC Thermistors (POSISTOR®) for Motor Starter Plug-in Type

●Product ID

| Product ID | |
|------------|-----------------|
| PT | PTC Thermistors |

2 Series

| Code | Series |
|------|---|
| Н7М | for Motor Starter Plug-in Type (Size ø16mm) |
| Н8М | for Motor Starter Plug-in Type (Size ø20mm) |
| нтм | for Motor Starter Enegy-saving Plug-in Type (Size ø16mm) |

3Resistance

Expressed by three figures. The units are ohms (Ω) . The first and second figures are significant digits, and the third figure expresses the number of zeros which follow the two figures. If there is a decimal point, it is expressed by the capital letter " \mathbf{R} ". In this case, all figures are significant digits.

| Ex.) | Code | Resistance |
|------|------|------------|
| | 4R7 | 4.7Ω |
| | 470 | 47Ω |

4 Resistance Tolerance

| Code | Resistance Tolerance |
|------|----------------------|
| М | ±20% |

5Starting Circuit

| Code | Starting Circuit |
|------|------------------|
| В3 | CSR 3Pin |
| C1 | RSIR 1Pin |
| C2 | RSIR 2Pin |
| D2 | RSCR 2Pin |
| D3 | RSCR 3Pin |

Please contact us for details.

6Individual Specifications

| Code | Individual Specifications |
|------|---------------------------|
| -00 | Structures, others |