



HARTING
Homepage

New
consulting

Help for
products

Help for
Harkis

Search in the partlist [Devices]

Search products by..

if necessary restrict the search on parts

Partlist

20 73 305 3921
ESC 67-30 TP05, Data 3A

Series	Ethernet Switch ESC 67-30 TP05U HARTING RJ Industrial® IP 67 Data 3A Ethernet Switch for the industrial applications
Protection level	IP 65/IP 67 outside the control cabinet IP 20 inside the control cabinet
Hood type	Robust metal housing of die cast aluminium alloy
Dimensions	105x40x120 (WxDxH in mm, without connectors)
Mounting	directly on control cabinets and terminal boxes
Operating temperature	-40 °C ... + 70 °C
Input voltage	24 V DC (18 ... 30 V DC)
Supply current	100 mA (at 24 V DC)
Terminals	Screw terminal with 5 contacts, plug-in redundant power supply
Data transmission rate	10 or 100 MBit/s / auto-negotiation
Cables	Shielded Twisted Pair (STP) or Unshielded-Twisted-Pair (UTP), Category 5
Ethernet Interface available device	Outside the control cabinet: 2x HARTING RJ Industrial® Data 3A connectors Inside the control cabinet: 3 x RJ 45 connectors
Max. cable length	auto-crossing function 100 m (Cat. 5) in acc. with EN 50 173

Inquiry

© Copyright 1999-2006 Harting KGaA and its licensors - Any suggestions and bug reports are welcome at: HARKIS@harting.com

Network Access Message: The page cannot be displayed

Explanation: The request timed out before the page could be retrieved.

Try the following:

- **Refresh page:** Search for the page again by clicking the Refresh button. The timeout may have occurred due to Internet congestion.
- **Check spelling:** Check that you typed the Web page address correctly. The address may have been mistyped.
- **Contact website:** You may want to contact the website administrator to make sure the Web page still exists. You can do this by using the e-mail address or phone number listed on the website home page.

If you are still not able to view the requested page, try contacting your administrator or Helpdesk.

Technical Information (for support personnel)

- Error Code 10060: Connection timeout
- Background: The gateway could not receive a timely response from the website you are trying to access. This might indicate that the network is congested, or that the website is experiencing technical difficulties.
- Date: 5/7/2006 11:19:12 AM
- Server: seba2.SiliconEgypt.com
- Source: Firewall