FAIRCHILD SEMICONDUCTOR®

RS1A - RS1M Fast Rectifiers

Features

- Glass passivated junction.
- For surface mounted applications.
- Built in strain relief, ideal for automated placement.
- UL certified with UL certificate # E326243.



SMA/DO-214AC COLOR BAND DENOTES CATHODE

Absolute Maximum Ratings* T_A = 25°C unless otherwise noted

| Symbol | Parameter | | Value | | | | | | |
|--------------------|--|-----------------------------|-------|------|----|----|----|----|-------|
| Symbol | | | 1B | 1D | 1G | 1J | 1K | 1M | Units |
| V _{RRM} | Maximum Repetitive Reverse Voltage | 50 100 200 400 600 800 1000 | | 1000 | V | | | | |
| I _{F(AV)} | Average Rectified Forward Current @ T _A = 100°C | 1.0 | | | | А | | | |
| I _{FSM} | Non-Repetitive Peak Forward Surge Current 8.3ms Single Half-Sine-Wave | | | А | | | | | |
| T _{STG} | Storage Temperature Range -55 to +150 | | | °C | | | | | |
| ТJ | Operating Junction Temperature | -55 to +150 | | °C | | | | | |

* These ratings are limiting values above which the serviceability of any semiconductor device may by impaired.

Thermal Characteristics

| Symbol | Parameter | Value | Units |
|---------------------|--|-------|-------|
| PD | Power Dissipation | 1.19 | W |
| R _{0JA} | Thermal Resistance, Junction to Ambient* | 105 | °C/W |
| $R_{	ext{	heta}JL}$ | Thermal Resistance, Junction to Lead* | 32 | °C/W |

* Device mounted on FR-4 PCB 0.013 mm.


Electrical Characteristics $T_A = 25^{\circ}C$ unless otherwise noted

| Symbol | Parameter | | Value | | | | | | | Units |
|-----------------|--|---|-------------|----|----|----------|----|----|----|-------|
| Symbol | | | 1A | 1B | 1D | 1G | 1J | 1K | 1M | Units |
| V _F | Forward Voltage @ 1.0A | | 1.3 | | | | | V | | |
| t _{rr} | Reverse Recovery Time I _F =0.5A, I _R =1.0A, I | _{rr} =0.25A | 150 250 500 | | | ns | | | | |
| I _R | Reverse Current @ rated V _R | T _A =25°C T _A =125°C | 5.0 50 | | | μΑ μΑ | | | | |
| CT | Total Capacitance V _R =4.0V, f=1.0MH | z | 10 | | pF | | | | | |

© 2011 Fairchild Semiconductor Corporation RS1A - RS1M Rev. D2

1

January 2011



RS1A - RS1M Rev. D2

RS1A - RS1M — Fast Rectifiers



SEMICONDUCTOR

TRADEMARKS

The following includes registered and unregistered trademarks and service marks, owned by Fairchild Semiconductor and/or its global subsidiaries, and is not intended to be an exhaustive list of all such trademarks.

Saving our world, 1mW/W/kW at a time™

| AccuPower TM Auto-SPM TM AX-CAP ^{TM*} Build it Now TM CorePLUS TM COREPOWER TM CROSSVOLT TM CTL TM CUTTent Transfer Logic TM DEUXPEED [®] Dual Cool TM EcoSPARK [®] EfficientMax TM ESBC TM Fairchild [®] Fairchild [®] Fairchild [®] Fairchild [®] Factor [®] FACT Quiet Series TM FACT [®] FAST [®] FastvCore TM FETBench TM FlashWriter ^{®*} | F-PFS™ FRFET® Global Power Resource SM Green FPS™ e-Series™ Gmax™ GTO™ InteliMAX™ ISOPLANAR™ MegaBuck™ MICROCOUPLER™ MicroPat2™ MicroPat2™ MicroPat2™ MicroPat2™ MotionMax™ Motion-SPM™ mWSaver™ OptoHIT™ OPTOLOGIC® OPTOPLANAR® | Power-SPM™ PowerTrench® PowerXS™ Programmable Active Droop™ QFET® QS™ Quiet Series™ RapidConfigure™ Saving our world, 1mW/W/kW a SignalWise™ SmartMax™ SMART START™ SPM® STEALTH™ SuperFET® SuperSOT™-6 SuperSOT™-6 SuperSOT™-8 SuperSOT SuperSot SuperSOT SuperSot SuperSOT SuperSOT SuperSot SuperSot SuperSOT Sup |
|--|--|--|
| EDOTM | PDF SPIN | OLNERAL |

FPS™

* Trademarks of System General Corporation, used under license by Fairchild Semiconductor.

DISCLAIMER

FAIRCHILD SEMICONDUCTOR RESERVES THE RIGHT TO MAKE CHANGES WITHOUT FURTHER NOTICE TO ANY PRODUCTS HEREIN TO IMPROVE RELIABILITY, FUNCTION, OR DESIGN. FAIRCHILD DOES NOT ASSUME ANY LIABILITY ARISING OUT OF THE APPLICATION OR USE OF ANY PRODUCT OR CIRCUIT DESCRIBED HEREIN; NEITHER DOES IT CONVEY ANY LICENSE UNDER ITS PATENT RIGHTS, NOR THE RIGHTS OF OTHERS. THESE SPECIFICATIONS DO NOT EXPAND THE TERMS OF FAIRCHILD'S WORLDWIDE TERMS AND CONDITIONS, SPECIFICALLY THE WARRANTY THEREIN, WHICH COVERS THESE PRODUCTS.

LIFE SUPPORT POLICY

FAIRCHILD'S PRODUCTS ARE NOT AUTHORIZED FOR USE AS CRITICAL COMPONENTS IN LIFE SUPPORT DEVICES OR SYSTEMS WITHOUT THE EXPRESS WRITTEN APPROVAL OF FAIRCHILD SEMICONDUCTOR CORPORATION.

As used herein:

- 1. Life support devices or systems are devices or systems which, (a) are intended for surgical implant into the body or (b) support or sustain life, and (c) whose failure to perform when properly used in accordance with instructions for use provided in the labeling, can be reasonably expected to result in a significant injury of the user.
- 2. A critical component in any component of a life support, device, or system whose failure to perform can be reasonably expected to cause the failure of the life support device or system, or to affect its safety or effectiveness.

The Power Franchise®

franchise bwer

TinyBoost™

TinyBuck™

TinyCalc™

TinyLogic® **TINYOPTO™** TinyPower™

TinyPWM™ TinyWire™

uSerDes™

UHC

TriFault Detect™ TRUECURRENT®*

Ultra FRFET™

UniFET™

VisualMax™

VCX™

XS™

The Right Technology for Your Success™

ANTI-COUNTERFEITING POLICY

Fairchild Semiconductor Corporation's Anti-Counterfeiting Policy. Fairchild's Anti-Counterfeiting Policy is also stated on our external website, www.fairchildsemi.com, under Sales Support.

Counterfeiting of semiconductor parts is a growing problem in the industry. All manufacturers of semiconductor products are experiencing counterfeiting of their parts. Customers who inadvertently purchase counterfeit parts experience many problems such as loss of brand reputation, substandard performance, failed applications, and increased cost of production and manufacturing delays. Fairchild is taking strong measures to protect ourselves and our customers from the proliferation of counterfeit parts. Fairchild strongly encourages customers to purchase Fairchild parts either directly from Fairchild or from Authorized Fairchild Distributors who are listed by country on our web page cited above. Products customers buy either from Fairchild directly or from Authorized Fairchild Distributors are genuine parts, have full traceability, meet Fairchild's quality standards for handling and storage and provide access to Fairchild's full range of up-to-date technical and product information. Fairchild and our Authorized Distributors will stand behind all warranties and will appropriately address any warranty issues that may arise. Fairchild will not provide any warranty coverage or other assistance for parts bought from Unauthorized Sources. Fairchild is committed to combat this global problem and encourage our customers to do their part in stopping this practice by buying direct or from authorized distributors

PRODUCT STATUS DEFINITIONS

| Definition | of Terms | |
|------------|----------|--|

| Datasheet Identification | Product Status | Definition |
|--------------------------|--------------------------|---|
| Advance Information | Formative / In Design | Datasheet contains the design specifications for product development. Specifications may change in any manner without notice. |
| Preliminary | First Production | Datasheet contains preliminary data; supplementary data will be published at a later date. Fairchild Semiconductor reserves the right to make changes at any time without notice to improve design. |
| No Identification Needed | Full Production | Datasheet contains final specifications. Fairchild Semiconductor reserves the right to make changes at any time without notice to improve the design. |
| Obsolete | Not In Production | Datasheet contains specifications on a product that is discontinued by Fairchild Semiconductor. The datasheet is for reference information only. |
| | | Rev. 153 |

© Fairchild Semiconductor Corporation

www.fairchildsemi.com