# 1-6609122-9 Product Details



1-6609122-9 (6EDL1S) TE Internal Number: 1-6609122-9



## **EMI/RFI Filters and Accessories**



# **Product Highlights:**

- Filter EMI/RFI
- Filter Type = Power Entry (Filtered/Unfiltered)
- L (2-6 Amp) Series
- General Purpose Application
- Mount Style = Flanged

View all Features

### **Documentation & Additional Information**

### **Product Drawings:**

• CUSTOMER DRAWING 6EDL1S (PDF, English)

### Catalog Pages/Data Sheets:

• Corcom L Series (PDF, English)

### **Product Specifications:**

None Available

### Application Specifications:

None Available

### **Instruction Sheets:**

None Available

### CAD Files:

None Available

#### Additional Information:

Product Line Information

### **Additional Product Images:**

Insertion Loss/Specifications

### **Related Products:**

Tooling

List all Documents

# Product Features (Please use the Product Drawing for all design activity)

# **Product Type Features:**

- Product Type = Filter EMI/RFI
- <u>Filter Type</u> = Power Entry (Filtered/Unfiltered)
- Filtered = Yes
- Connector Type = IEC 320/C14
- Comment = Voltage Fixed

### **Electrical Characteristics:**

- Current Rating (Amps.) = 6
- Voltage Selection = Single
- Voltage ≤ (VAC) = 120, 240
- Leakage Current (Line-to-Ground) Max. @ 250
  VAC 50 Hz (mA) = 0.5
- Leakage Current (Line-to-Ground) Max. @ 120
  VAC 60 Hz (mA) = 0.25

#### **Termination Related Features:**

- <u>Terminal Input Output Combination</u> = IEC
  - .110 Faston

### **Body Related Features:**

- <u>Series</u> = L (2-6 Amp)
- Mount Style = Flanged
- <u>Switch Type</u> = DPST

#### **Contact Related Features:**

 Approved Standards = UL Recognized, VDE Approved, CSA Certified

### **Configuration Related Features:**

- Fuse Options = Single
- Fuse Holder Type = North American

### **Industry Standards:**

- <u>RoHS/ELV Compliance</u> = RoHS compliant, ELV compliant
- <u>Lead Free Solder Processes</u> = Not relevant for lead free process
- RoHS/ELV Compliance History = Always was RoHS compliant

#### Conditions for Usage:

- Need Min Size With IEC Connector = Yes
- Need Optional Switch, Fusing, Or Voltage Selector = Yes

### Operation/Application:

• Application = General Purpose

### Other:

- Brand = Corcom
- Facility Installation = No