

## Data Sheet

### 10MHz Handheld Sine & Square Wave Signal Generator

**Model 3003**

#### Specifications

##### Frequency Characteristics

Waveforms	Sine, Square
Range	DC to 9.9999999MHz, 0.1Hz steps
Accuracy	0.02%
Sine Wave Output	0 – 4.5Vp-p (no load) Variable amplitude control
Output impedance	50 Ω
Square Wave Output	5Vp-p (no load)
Duty Cycle	50% typical
Output impedance	50 Ω
Power	An external AC adapter (6V - 9V DC 150mA 5.5mm x 2.1mm center pin+) or one 9V battery
Dimensions	1.5" x 3.8" x 5.7"



#### B&K Precision Corporation

22820 Savi Ranch Parkway, Yorba Linda, CA 92887  
Tel: 714-921-9095, Fax: 714-921-6422  
www.bkprecision.com

Specifications subject to change without notice