## CVC-190 B/W CCD Dual Voltage Camera with Built-in Electronic Iris



The CVC-190 is the only B/W camera you will ever need. It can operate on either a 12V DC or a 24V AC power supply (not included). It offers 420 lines of resolution with 0.02 lux sensitivity. It also has a 1/3 inch B/W image sensor, internal synchronization, and a built-in electronic shutter. It supports both video and DC drive auto iris lenses. The camera accommodates both C/CS lens types, sold separately

## **Specifications**

Resolution 420 lines
Minimum Illumination 0.02 lux
Image Device 1/3" B/W CCD

Electronic Shutter Auto 1/60 - 1/100,000 seconds

Lens Sold separately, accommodates C/CS type,

manual or auto iris

Video S/N Ratio Greater than 48 dB

Power Supply Requires a 12V DC or a 24V AC

power supply (not included)

Synchronization Line-locked in 24 Volts AC, V-phase adjustable

in 24 Volts AC, 2:1 internal in 12 Volts DC

Power Consumption 100 mA

Mounting 1/4-20, top and bottom Video Output 1.0 Vp-p 75 ohms

Outputs Video - BNC, Power - terminal strip

Operating Temperature 14°F to 122°F Humidity Within 95% RH

Scanning Frequency 15.75 kHz horizontal 60 Hz vertical

Dimensions 5"L x 2"W x 2"H

Weight 7 oz





Specifications subject to change