



# RECTIFIER-CONTROL-FILAMENT TRANSFORMERS



Part Number	Secondary		Primary Volts	Insulation Test RMS Volts	Style	Dimensions-Inches					Wt. Lbs.
	RMS					Case			Mounting		
	Volts	Amps				H	W	D	MW	MD	
23V256	24.OCT	0.085	117	1500	BAH	1 1/4	2 1/16	1 1/2	1 3/4	—	0.3
23V401	24.OCT	0.085	230	1500	BAH	1 1/4	2 1/16	1 3/8	1 3/4	—	0.3
23V257	24.OCT	0.20	117	1500	BAH	1 3/8	2 3/8	1 1/2	2	—	0.4
23V402	24.OCT	0.20	230	1500	BAH	1 3/8	2 3/8	1 1/2	2	—	0.4
23V258	24.OCT	0.40	117	1500	BAH	1 5/8	2 13/16	1 5/8	2 3/8	—	0.8
23V259	24.OCT	0.70	117	1500	BAH	2	3 1/4	1 3/4	2 13/16	—	0.9
23V404	24.OCT	0.70	230	1500	BAH	2	3 1/4	1 3/4	2 13/16	—	0.9
26F68	24.0	1.0	117	2500	BAH	2	3 1/4	2 1/8	2 13/16	—	1.5
21F84	24.OCT	1.0	115	1500	BAH	2	3 1/4	2 1/8	2 13/16	—	1.5
21F181	24.OCT	1.0	115/230	1500	BAH	2	3 5/16	2 1/8	2 13/16	—	1.5
23V552 S	24.0	2.0	115	1500	BAH	2 5/8	4	2 1/16	3 9/16	—	2.3
23V478	24.OCT	2.0	115	1500	BAH	2 5/8	4	2 3/8	3 9/16	—	2.3
23V419	24.OCT	4.0	117	1500	LAV	3 13/16	3 1/8	2 13/16	2 1/2	2 1/8	4.0
23V420	24.OCT	6.0	117	1500	LAV	4 3/16	3 7/16	3	2 3/4	2 1/4	5.7
23V421	24.OCT	8.0	117	1500	LAV	4 3/16	3 7/16	3 7/16	2 3/4	2 3/4	7.3
23V546	24.OCT	10.0	115	1500	LAV	4 3/16	3 1/2	3 1/4	2 3/4	3	8.0
23V422	24.OCT	12.0	117	1500	LAV	4 9/16	3 3/4	4 5/8	3	3 1/4	11.5
21F51	25.2	1.0	117	1500	BAH	2	3 1/4	2 1/8	2 13/16	—	1.5
21F159	25.2	1.0	230	1500	BAH	2	3 1/4	2 1/8	2 13/16	—	1.5
21F142	25.2CT	1.0	117	1500	BAH	2	3 1/4	2 1/8	2 13/16	—	1.5
21F83	25.2CT	2.0	115	1500	BAH	2 5/8	4	2 1/4	3 9/16	—	2.2
21F180	25.2CT	2.0	115/230	1500	BAH	2 5/8	4	2 1/4	3 9/16	—	2.2
21F114	25.2CT	3.0	117	1500	BAH	2 5/8	4	2 1/4	3 9/16	—	2.2
21F197	25.2CT	5.0	117	1500	GGV	4 1/4	3 7/16	3 7/8	2 3/4	2 11/16	5.5
21F198	25.2CT	7.5	117	1500	GGV	4 1/4	3 7/16	4 1/4	2 3/4	3 1/16	7.5
21F188 *	26.0OCT	0.04	117 *	2500	BAH	1 1/4	2 1/16	1 1/2	1 3/4	—	0.3
21F189 *	Nominal	0.25	117 *	2500	BAH	1 5/8	2 13/16	1 3/4	2 3/8	—	0.6
21F27	26.5CT	0.6	117	3000	BAH	2	3 1/4	2 1/8	2 13/16	—	1.6
21F82	26.8CT	1.0	115	1500	BAH	2	3 1/4	2 1/8	2 13/16	—	1.6
23V270	26.8CT	1.7	115	1500	BAH	2 5/8	4	2 1/4*	3 9/16	—	2.3
23V379	28.OCT	0.085	117	1500	BAH	1 1/4	2 1/16	1 3/8	1 3/4	—	0.3
23V381	28.OCT	0.3	117	1500	BAH	1 5/8	2 13/16	1 5/8	2 3/8	—	0.6
23V382	28.OCT	0.8	117	1500	BAH	2	3 1/4	2 1/8	2 13/16	—	1.0
23V423	28.OCT	1.0	117	1500	BAH	2	3 1/4	2 1/8	2 13/16	—	1.4
23V424	28.OCT	2.0	117	1500	LAV	3 1/8	2 1/2	2 1/2	2	2 3/16	2.9
23V425	28.OCT	4.0	117	1500	LAV	3 13/16	3 1/8	3 1/4	2 1/2	2 1/2	5.3
23V426	28.OCT	6.0	117	1500	LAV	4 3/16	3 7/16	3 1/2	2 3/4	2 5/8	7.0
23V479	30.OCT	1.0	115	1500	BAH	2 1/4	3 11/16	2	3 1/8	—	1.5
23V525	30.OCT	1.7	115	1500	BAH	2 5/8	4	2 1/4	3 9/16	—	1.5
23V480	30.OCT	2.0	115	1500	LAV	3 1/8	2 9/16	2 5/8	2	2 3/8	3.2
23V528	30.OCT	4.0	115	1500	LAV	3 7/8	3 1/8	3 1/8	2 1/2	2 5/8	5.8
23V531	30.OCT	1.5	115/230	1500	BAH	2 5/8	4	2 5/16	3 9/16	—	2.2
23V384	36.OCT	0.065	117	1500	BAH	1 1/4	2 1/8	1 3/8	1 3/4	—	0.3
23V405	36.OCT	0.065	230	1500	BAH	1 1/4	2 1/8	1 3/8	1 3/4	—	0.3
23V385	36.OCT	0.135	117	1500	BAH	1 3/8	2 3/8	1 7/16	2	—	0.4
23V386	36.OCT	0.3	117	1500	BAH	1 5/8	2 13/16	1 5/8	2 3/8	—	0.7
23V387	36.OCT	0.55	117	1500	BAH	2	3 1/4	1 7/8	2 13/16	—	1.0
23V427	36.OCT	1.0	117	1500	LAV	2 3/8	3 3/4	2 3/8	3 1/8	—	2.0
23V428	36.OCT	2.0	117	1500	LAV	3 7/16	2 13/16	2 3/4	2 1/4	2 1/8	3.4
23V429	36.OCT	4.0	117	1500	LAV	4 3/16	3 7/8	3 1/8	2 3/4	2 3/8	6.1
23V430	36.OCT	6.0	117	1500	LAV	4 9/16	3 3/4	3 5/8	3	2 5/8	8.5
23V520	40.OCT	0.12	115/230	2500	BAH	1 3/8	2 3/8	1 3/8	2	—	0.5
23V521	40.OCT	0.2	115/230	2500	BAH	1 5/8	2 13/16	1 1/2	2 3/8	—	0.6
23V522	40.OCT	0.25	115/230	2500	BAH	1 5/8	2 13/16	1 5/8	2 3/8	—	0.8
23V458	40.OCT	1.0	115	1500	BAH	2 5/8	4	2 5/16	3 9/16	—	2.6
23V459	40.OCT	2.0	115	1500	LAV	3 1/2	2 7/8	2 7/8	2 1/4	2 3/8	4.0
23V529	40.OCT	4.0	115	1500	LAV	3 7/8	3 1/8	3 1/2	2 1/2	2 7/8	6.3
21F187 **	48.OCT	1.0	117 **	2500	BAH	2 5/8	4	2 3/8	3 9/16	—	2.3
23V466	Nominal	1.0	115	1500	BAH	2 5/8	4	2 5/16	3 9/16	—	2.5
23V530	50.OCT	4.0	115	1500	LAV	4 3/16	3 7/16	3 1/2	2 3/4	2 3/4	7.5
23V523	60.OCT	0.4	115	1500	BAH	2	3 1/4	2	2 13/16	—	1.3
23V464	60.OCT	1.0	115	1500	LAV	3	2 1/2	2 5/16	2	2 3/8	3.4
23V465	60.OCT	2.0	115	1500	LAV	3 13/16	3 1/8	2 7/8	2 1/2	2 5/8	5.7
23V468	70.OCT	1.0	115	1500	LAV	3 1/2	2 7/8	3 1/2	2 1/4	2 1/4	4.1

