





AMC7110/1/3/4

White/Blue LED Driver for Li-Ion Battery Application

DESCRIPTION	FEATURES															
<p>The AMC7110 series is member of ADDM North Star White/Blue LED driver family. No external component is required. Especially good for use Li-ion battery powered LCD display's backlight white LEDs. The special circuit design provides over 90% efficiency in low noise.</p> <p>Target end applications are color LCD display, such as mobile phone with color display, smart phone, PDA, etc.</p> <table border="1" style="margin-left: auto; margin-right: auto;"> <thead> <tr> <th>Device Name</th> <th>LED Sink Current</th> <th>LED Number</th> </tr> </thead> <tbody> <tr> <td>AMC7110</td> <td>20mA</td> <td>3</td> </tr> <tr> <td>AMC7111</td> <td>20mA</td> <td>4</td> </tr> <tr> <td>AMC7113</td> <td>15mA</td> <td>3</td> </tr> <tr> <td>AMC7114</td> <td>15mA</td> <td>4</td> </tr> </tbody> </table>	Device Name	LED Sink Current	LED Number	AMC7110	20mA	3	AMC7111	20mA	4	AMC7113	15mA	3	AMC7114	15mA	4	<ul style="list-style-type: none"> ■ No external component required. ■ LED sink current 20 mA and 15mA ■ Individual current sink circuit for all LEDs outputs to prevent short / open circuit on LEDs. ■ PTC LED current for luminosity compensation. ■ 3 channels (SOT-26), 4 channels (MSOP-8) available. ■ 90% efficiency ■ Supply voltage range 2.7V ~ 6V ■ 0.1uA standby current ■ 2KV HBM ESD protection ■ Advanced Bi-CMOS process
Device Name	LED Sink Current	LED Number														
AMC7110	20mA	3														
AMC7111	20mA	4														
AMC7113	15mA	3														
AMC7114	15mA	4														
	APPLICATIONS															
	<ul style="list-style-type: none"> ■ Small Size Color LCD Backlights ■ Mobile Phone, Smart Phone Keypad Backlights. 															
PACKAGE PIN OUT																



AMC7110, AMC7113
SOT-26



AMC7111, AMC7114
MSOP-8

ORDER INFORMATION			
T_A (°C)	DB	Plastic SOT-26	DN
		6-pin	
0 to 70		AMC7110DB	AMC7111DN
0 to 70		AMC7113DB	AMC7114DN
Note: Surface-mount packages is available in Tape & Reel. Append "T" to part number (i.e., AMC7111DNT). DB is only available in Tape & Reel. Append "T" to part number (i.e., AMC7110DBT).			