GV2ME06

Manual Motor Starter and Protector (TeSys GV2) Pushbutton, Trip: 1.0A to 1.6A

List Price \$180.00 USD

Availability Stock Item: This item is normally stocked in our distribution facility.

Technical Characteristics

| Horsepower Rating (1-Phase) | 0.01HP@230VAC |
|-----------------------------|---|
| Maximum Voltage Rating | 600VAC |
| Mounting Type | Panel |
| Number of Poles | 3-Pole |
| Starter Type | Non-Reversing |
| Thermal Trip Setting | 1.0A to 1.6A |
| Туре | GV2 |
| Horsepower Rating (3-Phase) | 0.75HP@460VAC - 1HP@575VAC |
| Marketing Trade Name | TeSys |
| Operator Type | Pushbutton |
| Overload Type | Ambient Compensated Bimetallic (Class 10) |
| Interrupt Rating | Standard |
| Terminal Type | Screw Clamp |
| Approvals | UL Listed File Number: E164864 NLRV - CSA Certified File Number: LR81630 Class: 3211 05 - CE Marked |
| | |

Shipping and Ordering

| Category | 22367 - Protectors, Starter, Manual, Type GV2 |
|-------------------|---|
| Discount Schedule | 111 |
| GTIN | 00785901211938 |
| Package Quantity | 1 |
| Weight | 0.57 lbs. |
| Availability Code | Stock Item: This item is normally stocked in our distribution facility. |
| Returnability | Y |
| Country of Origin | FR |

As standards, specifications, and designs change from time to time, please ask for confirmation of the information given in this document.

Generated: 11/03/2011 01:05:47

